

802.11j™

**IEEE Standard for
Information technology—
Telecommunications and information
exchange between systems—
Local and metropolitan area networks—
Specific requirements**

**Part 11: Wireless LAN Medium Access Control
(MAC) and Physical Layer (PHY) specifications**

Amendment 7: 4.9 GHz–5 GHz Operation in Japan

IEEE Computer Society

Sponsored by the
LAN/MAN Standards Committee

This amendment is an approved IEEE
Standard. It will be incorporated into the
base standard in a future edition.



IEEE Std 802.11j™-2004

[Amendment to IEEE Std 802.11™, 1999 Edition (Reaff 2003)
as amended by IEEE Stds 802.11a™-1999, 802.11b™-1999,
802.11b™-1999/Cor 1-2001, 802.11d™-2001,
802.11g™-2003, 802.11h™-2003, and 802.11i™-2004]

**IEEE Standard for
Information technology—
Telecommunications and information
exchange between systems—
Local and metropolitan area networks—
Specific requirements**

**Part 11: Wireless LAN Medium Access Control (MAC)
and Physical Layer (PHY) Specifications**

**Amendment 7: 4.9 GHz–5 GHz Operation
in Japan**

Sponsor
LAN/MAN Committee
of the
IEEE Computer Society

Approved 23 September 2004

IEEE-SA Standards Board

Abstract: This amendment specifies the extensions to IEEE Std 802.11 for wireless local area networks (WLANs) providing mechanisms for operation in the 4.9 GHz and 5 GHz bands in Japan.
Keywords: LAN, local area network, regulatory class

The Institute of Electrical and Electronics Engineers, Inc.
3 Park Avenue, New York, NY 10016-5997, USA

Copyright © 2004 by the Institute of Electrical and Electronics Engineers, Inc.
All rights reserved. Published 29 October 2004. Printed in the United States of America.

IEEE and 802 are registered trademarks in the U.S. Patent & Trademark Office, owned by the Institute of Electrical and Electronics Engineers, Incorporated.

Print: ISBN 0-7381-4464-9 SH95267
PDF: ISBN 0-7381-4465-7 SS95267

No part of this publication may be reproduced in any form, in an electronic retrieval system or otherwise, without the prior written permission of the publisher.

IEEE Standards documents are developed within the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Association (IEEE-SA) Standards Board. The IEEE develops its standards through a consensus development process, approved by the American National Standards Institute, which brings together volunteers representing varied viewpoints and interests to achieve the final product. Volunteers are not necessarily members of the Institute and serve without compensation. While the IEEE administers the process and establishes rules to promote fairness in the consensus development process, the IEEE does not independently evaluate, test, or verify the accuracy of any of the information contained in its standards.

Use of an IEEE Standard is wholly voluntary. The IEEE disclaims liability for any personal injury, property or other damage, of any nature whatsoever, whether special, indirect, consequential, or compensatory, directly or indirectly resulting from the publication, use of, or reliance upon this, or any other IEEE Standard document.

The IEEE does not warrant or represent the accuracy or content of the material contained herein, and expressly disclaims any express or implied warranty, including any implied warranty of merchantability or fitness for a specific purpose, or that the use of the material contained herein is free from patent infringement. IEEE Standards documents are supplied “**AS IS.**”

The existence of an IEEE Standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE Standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard. Every IEEE Standard is subjected to review at least every five years for revision or reaffirmation. When a document is more than five years old and has not been reaffirmed, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE Standard.

In publishing and making this document available, the IEEE is not suggesting or rendering professional or other services for, or on behalf of, any person or entity. Nor is the IEEE undertaking to perform any duty owed by any other person or entity to another. Any person utilizing this, and any other IEEE Standards document, should rely upon the advice of a competent professional in determining the exercise of reasonable care in any given circumstances.

Interpretations: Occasionally questions may arise regarding the meaning of portions of standards as they relate to specific applications. When the need for interpretations is brought to the attention of IEEE, the Institute will initiate action to prepare appropriate responses. Since IEEE Standards represent a consensus of concerned interests, it is important to ensure that any interpretation has also received the concurrence of a balance of interests. For this reason, IEEE and the members of its societies and Standards Coordinating Committees are not able to provide an instant response to interpretation requests except in those cases where the matter has previously received formal consideration. At lectures, symposia, seminars, or educational courses, an individual presenting information on IEEE standards shall make it clear that his or her views should be considered the personal views of that individual rather than the formal position, explanation, or interpretation of the IEEE.

Comments for revision of IEEE Standards are welcome from any interested party, regardless of membership affiliation with IEEE. Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments. Comments on standards and requests for interpretations should be addressed to:

Secretary, IEEE-SA Standards Board
445 Hoes Lane
Piscataway, NJ 08854 USA

NOTE—Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken with respect to the existence or validity of any patent rights in connection therewith. The IEEE shall not be responsible for identifying patents for which a license may be required by an IEEE standard or for conducting inquiries into the legal validity or scope of those patents that are brought to its attention.

Authorization to photocopy portions of any individual standard for internal or personal use is granted by the Institute of Electrical and Electronics Engineers, Inc., provided that the appropriate fee is paid to Copyright Clearance Center. To arrange for payment of licensing fee, please contact Copyright Clearance Center, Customer Service, 222 Rosewood Drive, Danvers, MA 01923 USA; +1 978 750 8400. Permission to photocopy portions of any individual standard for educational classroom use can also be obtained through the Copyright Clearance Center.

Introduction

[This introduction is not part of IEEE Std 802.11j-2004, IEEE Standard for Information Technology—Telecommunications and Information Exchange Between Systems—Local and Metropolitan Area Networks—Specific Requirements—Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications—Amendment 7: 4.9 GHz–5 GHz Operation in Japan.]

IEEE Std 802.11j-2004 provides mechanisms for signalling compliance with regulatory domain requirements of the USA, Europe, and Japan; for extending 5 GHz orthogonal frequency division multiplexing (OFDM) physical layer (PHY) operation outdoors; and for 5 GHz OFDM PHY operation in nonoverlapping 10 MHz channel spacing.

Notice to users

Errata

Errata, if any, for this and all other standards can be accessed at the following URL: <http://standards.ieee.org/reading/ieee/updates/errata/index.html>. Users are encouraged to check this URL for errata periodically.

Interpretations

Current interpretations can be accessed at the following URL: <http://standards.ieee.org/reading/ieee/interp/index.html>.

Patents

Attention is called to the possibility that implementation of this standard may require use of subject matter covered by patent rights. By publication of this standard, no position is taken with respect to the existence or validity of any patent rights in connection therewith. The IEEE shall not be responsible for identifying patents or patent applications for which a license may be required to implement an IEEE standard or for conducting inquiries into the legal validity or scope of those patents that are brought to its attention.

Participants

At the time the draft of this amendment was sent to sponsor ballot, the IEEE 802.11 Working Group had the following officers:

Stuart J. Kerry, *Chair*

Al Petrick and Harry Worstell, *Vice-Chairs*

Tim Godfrey, *Secretary*

Brian Mathews, *Publicity Standing Committee*

Teik-Kheong Tan, *Wireless Next Generation Standing Committee*

Terry L. Cole, *Editor*

John Fakatselis, Chair Task Group e
Duncan Kitchen, Vice-Chair Task Group e
David Halasz, Chair Task Group i
Richard Paine, Chair Task Group k
Bob O'Hara, Chair Task Group m
Bruce Kramer, Chair Task Group n

When the IEEE 802.11 Working Group approved this amendment, the Task Group j had the following membership:

Sheung Li, Chair

Peter Ecclesine, Editor

Albert Garrett, Christopher Hansen, Andrew Myles, and Stephen P. Pope, Secretaries

Osama Aboul-Magd	Harry Bims	Simon Duggins
Tomoko Adachi	Bjorn Bjerke	Baris Dunder
Jaemin Ahn	Simon Black	Bryan Dunn
Thomas Alexander	Jan Boer	Roger Durand
Areg Alimian	William Brasier	Eryk Dutkiewicz
Richard Allen	Jennifer Bray	Mary DuVal
Keith Amann	Phillip Brownlee	Yaron Dycian
Dov Andelman	Alex Bugeja	Donald Eastlake
Merwyn Andrade	Alistair Buttar	Dennis Eaton
Carl Andren	Peter Cain	Jonathan Edney
David Andrus	Richard Cam	Bruce Edwards
Butch Anton	Nancy Cam-Winget	Natarajan Ekambaram
Hidenori Aoki	Bill Carney	Jason Ellis
Tsuguhide Aoki	Pat Carson	Darwin Engwer
Michimasa Aramaki	Broady Cash	Jeff Erwin
Takashi Aramaki	Jayant Chande	Andrew Estrada
William Arbaugh	Kisoo Chang	Christoph Euscher
Lee Armstrong	Clint Chaplin	Knut Evensen
Larry Arnett	Ye Chen	John Fakatselis
Hiroshi Asai	Hong Cheng	Lars Falk
Yusuke Asai	Greg Chesson	Steve Fantaste
Arthur Astrin	Aik Chindapol	Paul Feinberg
Malik Audeh	Sunghyun Choi	Alex Feldman
Geert Awater	Won-Joon Choi	Weishi Feng
Shahmaz Azizi	Woo-Yong Choi	Nestor Fesas
Floyd Backes	Yang-Seok Choi	Matthew Fischer
Jin-Seok Bae	Per Christoffersson	Wayne Fisher
David Bagby	Simon Chung	Helena Flygare
Jay Bain	Ken Clements	Brian Ford
Dennis Baker	Sean Coffey	Ruben Formoso
Ramanathan Balachander	Terry Cole	Sheila Frankel
Jaiganesh Balakrishnan	Paul Congdon	John Fuller
Boyd Bangerter	W. Steven Conner	James Gardner
John Barr	Charles Cook	Atul Garg
Simon Barber	Kenneth Cook	Ramez Gerges
Farooq Bari	Todor Cooklev	Noam Geri
Michael Barkway	Mary Cramer	Vafa Ghazi
Kevin Barry	Steven Crowley	Monisha Ghosh
Anuj Batra	Nora Dabbous	James Gilb
Burak Baysal	Rolf De Vegt	Jeffrey Gilbert
Tomer Bentzion	Javier Del Prado Pavon	Rabinder Gill
Mathilde Benveniste	Georg Dickmann	Tim Godfrey
Don Berry	Wim Diepstraten	Wataru Gohda
Jan Biermann	Yoshiharu Doi	Yuri Goldstein
Arnold Bilstad	Brett Douglas	Jim Goodman

Aviv Goren	Taehyun Jeon	Quinn LI
Andrew Gowans	Moo Ryong Jeong	Jie Liang
Rik Graulus	Daniel Jiang	Wei Lih Lim
Gordon Gray	Kuniko Jimi	Yong Je Lim
Evan Green	Walter Johnson	Huashih Lin
Larry Green	David Johnston	Sheng Lin
Patrick Green	Jari Jokela	Victor Lin
Kerry Greer	VK Jones	Stanley Ling
Daqing Gu	Bobby Jose	Der-Zheng Liu
Rajugopal Gubbi	Tyan-Shu Jou	I-Ru Liu
Sam Guirguis	Carl Kain	Yonghe Liu
Srikanth Gummadi	Srinivas Kandala	Titus Lo
Qiang Guo	You Sung Kang	Peter Loc
Vivek Gupta	Jeyhan Karaoguz	Patrick Lopez
Herman Haisch	Kevin Karcz	Hui-Ling Lou
David Halasz	Pankaj Karnik	Xiaolin Lu
Steven Halford	Mika Kasslin	Luke Ludeman
Robert Hall	Dean Kawaguchi	Yi-Jen Lung
Neil Hamady	Patrick Kelly	Akira Maeki
Mounir Hamdi	Richard Kennedy	Ravishankar Mahadevappa
Yasuo Harada	Stuart Kerry	Doug Makishima
Daniel Harkins	John Ketchum	Majid Malek
Thomas Haslestad	Vytas Kezys	Rahul Malik
Amer Hassan	Andrew Khieu	Jouni Malinen
Vann Hasty	Ryoji Kido	Krishna Malladi
James Hauser	Tomohiro Kikuma	Stefan Mangold
Yutaka Hayakawa	Byoung-Jo Kim	Mahalingam Mani
Morihiko Hayashi	Dooseok Kim	Jonn Martell
Haixiang He	Joonsuk Kim	Naotaka Maruyama
Xiaoning He	Yongbum Kim	Paul Marzec
Robert Heile	Yongsuk Kim	Brian Mathews
Eleanor Hepworth	Young Kim	Yoichi Matsumoto
Frans Hermodsson	Youngsoo Kim	Sudheer Matta
Dave Hetherington	Wayne King	Thomas Maufer
Guido Hiertz	John Klein	Conrad Maxwell
Garth Hillman	Guenther Kleindl	Stephen McCann
Christopher Hinsz	Toshiya Kobashi	Kelly McClellan
Jun Hirano	Keiichiro Koga	Gary McCoy
Mikael Hjelm	Lalit Kotecha	William McFarland
Jin-Meng Ho	John Kowalski	Timothy McGovern
Michael Hoghooghi	Bruce Kraemer	Bill McIntosh
Allen Hollister	Gopal Krishnan	Justin McNew
Keith Holt	Shuji Kubota	Irina Medvedev
Satoru Hori	Thomas Kuehnel	Pratik Mehta
William Home	Tomoaki Kumagai	Robert Meier
Srinath Hosur	Takushi Kunihiro	Graham Melville
Russell Housley	Thomas Kurihara	Klaus Meyer
Frank Howley	Denis Kuwahara	Robert Miller
Yungping Hsu	Joe Kwak	Partho Mishra
Robert Huang	Paul Lambert	David Mitton
Dave Hudak	David Landeta	Kenichi Miyoshi
David Hunter	Jim Lansford	Rishi Mohindra
Syang-Myau Hwang	Colin Lanzl	Peter Molnar
David Hytha	Jon LaRosa	Leo Monteban
Muhammad Ikram	Choi Law	Michael Montemurro
Daichi Imamura	David Leach	Rondal Moore
Kimihiko Imamura	Dongjun Lee	Tim Moore
Yasuhiko Inoue	Insun Lee	Anthony Morelli
Katsumi Ishii	Jae Hwa Lee	Mike Moreton
Stephen Jackson	Marty Lefkowitz	Yuichi Morioka
Eric Jacobsen	Onno Letanche	Steven Morley
Marc Jalfon	Joseph Levy	Robert Moskowicz
Kyung-Hun Jang	Mike Lewis	Joseph Mueller
Bruno Jechoux	Pen Li	Syed Mujtaba

Willem Mulder	Edward Reuss	Shravan Surineni
Peter Murphy	Valentine Rhodes	Hirokazu Tagiri
Peter Murray	Maximilian Riegel	Masahiro Takagi
Andrew Myers	Edmund Ring	Mineo Takai
Yukimasa Nagai	Carlos Rios	Katsumi Takaoka
Katsuyoshi Naka	Stefan Rommer	Daisuke Takeda
Makoto Nakahara	Jon Rosdahl	Nir Tal
Michiharu Nakamura	John Sadowsky	Tsuyoshi Tamaki
Seigo Nakao	Ali Sadri	Pek-Yew Tan
Hiroyuki Nakase	Kazuyuki Sakoda	Teik-Kheong Tan
Sanjiv Nanda	Shoji Sakurai	Wai-Cheung Tang
Ravi Narasimhan	Kenichi Sakusabe	Takuma Tanimoto
Slobodan Nedic	Hemanth Sampath	Henry Taylor
Robert Neilsen	Sumeet Sandhu	James Taylor
David Nelson	Anil Sanwalka	Carl Temme
Dan Nemits	Ryo Sawai	Stephan ten Brink
Chiu Ngo	Tom Schaffnit	John Terry
Tuan Nguyen	Brian Schreder	Timothy Thornton
Qiang Ni	Sid Schrum	Jerry Thrasher
Gunnar Nitsche	Erik Schylander	James Tomcik
Erwin Noble	Michael Seals	Allen Tsai
Tzvetan Novkov	Joe Sensendorf	Jean Tsao
Ivan Oakes	N. Shankaranarayanan	Chih Tsien
Kei Obara	Donald Shaver	Tom Tsoulogiannis
Karen O'Donoghue	Stephen Shellhammer	Kwei Tu
Hiroshi Oguma	Tamara Shelton	David Tung
Jongtaek Oh	Yangmin Shen	Sandra Turner
Bob O'Hara	Ian Sherlock	Mike Tzamaloukas
Sean O'Hara	Matthew Sherman	Marcos Tzannes
Yoshihiro Ohtani	Ming Sheu	Yusuke Uchida
Chandra Olson	Shusaku Shimada	Takashi Ueda
Timothy Olson	Matthew Shoemake	Naoki Urano
Hiroshi Ono	William Shvodian	Hidemi Usuba
Peter Oomen	D. J. Shyy	Chandra Vaidyanathan
Lior Ophir	Thomas Siep	Hans Van Leeuwen
Satoshi Oyama	Floyd Simpson	Richard van Leeuwen
Richard Paine	Manoneet Singh	Richard Van Nee
Michael Paljug	Hasse Sinivaara	Nico van Waes
Stephen Palm	Efstratios (Stan) Skafidas	Allert van Zelst
Jong Ae Park	David Skellern	Narasimhan Venkatesh
Jonghun Park	Roger Skidmore	Madan Venugopal
Joon Goo Park	Donald Sloan	George Vlantis
Taegon Park	Kevin Smart	Dennis Volpano
Steve Parker	David Smith	Tim Wakeley
Glenn Parsons	Yoram Solomon	Jesse Walker
Vijay Patel	V. Somayazulu	Brad Wallace
Eldad Perahia	Amjad Soomro	Thierry Walrant
Sebastien Perrot	Robert Soranno	Vivek Wandile
Al Petrick	Gary Spiess	Huaiyuan (Stephen) Wang
Joe Pitarresi	William Spurgeon	Stanley Wang
Leo Pluswick	Dorothy Stanley	Christopher Ware
James Portaro	William Steck	Fujio Watanabe
Al Potter	Greg Steele	Mark Webster
Henry Ptasinski	Adrian Stephens	Matthew Welborn
Anuj Puri	William Stevens	Bryan Wells
Aleksandar Purkovic	Carl Stevenson	Filip Weytjens
Jim Raab	Fred Stivers	Stephen Whitesell
Ali Raissinia	Warren Strand	Michael WilhoYTE
Ajay Rajkumar	Paul Struhsaker	Michael Glenn Williams
Noman Rangwala	Michael Su	Peter Williams
Ivan Reede	Hiroki Sugimoto	Richard Williams
Stanley Reible	Abhaya Sumanasena	James Wilson
Anthony Reid	Qinfang Sun	Steven Wilson
Joe Repice	S. K. Sung	Jack Winters

Jin Kue Wong
Timothy Wong
Patrick Worfolk
Harry Worstell
Charles Wright
Gang Wu

Yang Xiao
James Yee
Jung Yee
Kazim Yildiz
Jijun Yin
Kit Yong
Wonyong Yoon

Heejung Yu
Hon Yung
Erol Yurtkuran
Zhun Zhong
Glen Zorn
James Zyren

Major contributions were received from the following individuals:

Tomoko Adachi
Peter Ecclesine
Darwin A. Engwer
Albert Garrett
Christopher Hansen

Yasuhiko Inoue
Uriel Lemberger
Sheung Li
William McFarland
Andrew Myles

Gunnar Nitsche
Tomoki Ohsawa
Kazuhiro Okanoue
Stephen P. Pope
Masahiro Takagi

This amendment was balloted using individual balloting. The following members of the balloting committee voted on this amendment. Balloters may have voted for approval, disapproval, or abstention.

Tomoko Adachi
Toru Aihara
Wole Akpose
Thomas Alexander
Butch Anton
Eladio Arvelo
Jennifer Bray
William Byrd
Clint Chaplin
Keith Chow
Terry L. Cole
Javier del Prado Pavon
Thomas Dineen
Sourav Dutta
Peter Ecclesine
Darwin A. Engwer
Theodore Georgantas
Ron Greenthaler
Qiang Guo
Jose Gutierrez
Zion Hadad
David Halasz
Atsushi Ito
Yasuhiko Inoue
Peeya Iwagoshi
Raj Jain
David James

David Johnston
Bobby Jose
Kevin Karcz
Ruediger Kays
Stuart Kerry
Joshua Kilgore
Guenter Kleindl
Cees Klik
Thomas M. Kurihara
Denis Kuwahara
Jeremy Landt
Jan-Ray Liao
Randolph Little
William Lumpkins
Ben Manny
Justin McNew
Ingolf Meier
Yinghua Min
Leo Monteban
Mike Moreton
Narayanan Murugesan
Andrew Myles
Paul Nikolich
Erwin Noble
Bob O'Hara
Stephen Palm

Roger Pandanda
Subbu Ponnuswamy
Vikram Punj
Maximilian Riegel
Randal Roebuck
Osman Sakr
Vaughn Sheline
Gil Shultz
Amjad Soomro
Robert Soranno
Thomas Starai
Adrian Stephens
Carl Stevenson
Mark-Rene Uchida
Scott Valcourt
Richard van Leeuwen
Tom Wandeloski
Stanley Wang
William Ward
Menzo Wentink
Filip Weytjens
Stephen Whitesell
Harry R. Worstell
Jung Yee
Patrick Yu
Oren Yuen
Surong Zeng

When the IEEE-SA Standards Board approved this amendment on 23 September 2004, it had the following membership:

Don Wright, *Chair*
Steve M. Mills, *Vice Chair*
Judith Gorman, *Secretary*

Chuck Adams
H. Stephen Berger
Mark D. Bowman
Joseph A. Bruder
Bob Davis
Roberto de Boisson
Julian Forster*
Arnold M. Greenspan

Mark S. Halpin
Raymond Hapeman
Richard J. Holleman
Richard H. Hulett
Lowell G. Johnson
Joseph L. Koepfinger*
Hermann Koch
Thomas J. McGean
Daleep C. Mohla

Paul Nikolich
T. W. Olsen
Ronald C. Petersen
Gary S. Robinson
Frank Stone
Malcolm V. Thaden
Doug Topping
Joe D. Watson

*Member Emeritus

Also included are the following nonvoting IEEE-SA Standards Board liaisons:

Satish K. Aggarwal, *NRC Representative*
Richard DeBlasio, *DOE Representative*
Alan Cookson, *NIST Representative*

Michael Fisher
IEEE Standards Project Editor

Contents

3.	Definitions	1
7.	Frame formats	2
7.3	Management frame body components	2
7.3.2	Information elements	2
7.3.2.12	Country information element	2
10.	Layer management	4
10.3	Medium access control (MAC) sublayer management entity (MLME) service access point (SAP) interface	4
10.3.2	Scan	4
10.3.2.2	MLME-SCAN.confirm	4
10.3.10	Start	5
10.3.10.2	MLME-START.confirm	5
11.	MLME	5
11.1	Synchronization	5
11.1.3	Acquiring synchronization, scanning	5
17.	Orthogonal frequency division multiplexing (OFDM) physical layer (PHY) specification for the 5 GHz band	6
17.1	Introduction	6
17.2	OFDM PHY specific service parameter list	6
17.2.2	TXVECTOR parameters	6
17.2.2.2	TXVECTOR.DATARATE	7
17.2.3	RXVECTOR parameters	7
17.2.3.3	DATARATE	7
17.3	OFDM physical layer convergence procedure (PLCP) sublayer	8
17.3.2	PLCP frame format	8
17.3.2.1	Overview of the PLCP protocol data unit (PPDU) encoding process	8
17.3.2.2	ModulationRate-dependent parameters	8
17.3.2.3	Timing-related parameters	9
17.3.2.4	Mathematical conventions in the signal descriptions	9
17.3.3	PLCP preamble (SYNC)	9
17.3.4	Signal field (SIGNAL)	10
17.3.4.1	Data rate	10
17.3.7	PLCP data modulation and modulation rate change	10
17.3.8	Physical medium dependent (PMD) operating specifications (general)	11
17.3.8.1	Outline description	11
17.3.8.2	Regulatory requirements	11
17.3.8.3	Operating channel frequencies	12
17.3.8.4	Transmit and receive in-band and out-of-band spurious emissions	14
17.3.8.6	Slot time	14
17.3.9	PMD transmit specifications	14
17.3.9.1	Transmit power levels	14
17.3.9.2	Transmit spectrum mask	15
17.3.9.6	Modulation accuracy	15

17.3.10	PMD receiver specifications	16
17.3.10.1	Receiver minimum input level sensitivity	16
17.3.10.5	CCA sensitivity	16
17.4	OFDM PLME	16
17.4.2	OFDM PHY MIB	16
17.4.3	OFDM TXTIME calculation	17
17.4.4	OFDM PHY characteristics	17
17.5	OFDM PMD sublayer	18
17.5.4	Basic service and options	18
17.5.4.3	PMD_SAP service primitive parameters	18
Annex A (normative) Protocol Implementation Conformance Statements (PICS)		20
A.4	PICS proforma—IEEE Std 802.11, 1999 Edition (<u>Reaff 2003</u>)	20
A.4.3	Implementation under test (IUT) configuration	20
A.4.8	Orthogonal frequency division multiplex (OFDM) physical layer (PHY) functions	20
A.4.10	Regulatory domain extensions	24
A.4.13	Regulatory classes extensions	24
Annex D (normative) ASN.1 encoding of the MAC and PHY MIB		25
Annex I (informative) Regulatory classes		31
I.1	External regulatory references	31
I.2	Radio performance specifications	33
I.2.1	Transmit and receive in-band and out-of-band spurious emissions	33
I.2.2	Transmit power levels	35
I.2.3	Transmit spectrum mask	36
Annex J (normative) Country information element and regulatory classes		38

**IEEE Standard for
Information technology—
Telecommunications and information
exchange between systems—
Local and metropolitan area networks—
Specific requirements**

**Part 11: Wireless LAN Medium Access Control (MAC)
and Physical Layer (PHY) Specifications**

**Amendment 7: 4.9 GHz–5 GHz Operation
in Japan**

[This amendment is based on IEEE Std 802.11™, 1999 Edition (Reaff 2003), as amended by IEEE Stds 802.11a™-1999, 802.11b™-1999, 802.11b™-1999/Cor 1-2001, 802.11d™-2001, 802.11g™-2003, 802.11h™-2003, and 802.11i™-2004.]

NOTE—The editing instructions contained in this amendment define how to merge the material contained herein into the existing base standard and its other amendments to form the comprehensive standard.

The editing instructions are shown in *bold italic*. Four editing instructions are used: change, delete, insert, and replace. *Change* is used to make small corrections in existing text or tables. The editing instruction specifies the location of the change and describes what is being changed either by using ~~strike through~~ (to remove old material) or underscore (to add new material). *Delete* removes existing material. *Insert* adds new material without disturbing the existing material. Insertions may require renumbering. If so, renumbering instructions are given in the editing instructions. *Replace* is used to make large changes in existing text, subclauses, tables, or figures by removing existing material and replacing it with new material. Editorial notes will not be carried over into future editions.

3. Definitions

Insert the following definition in alphabetical order into Clause 3, renumbering as necessary:

3.122 channel spacing: Nonoverlapping, adjacent channel, center frequency spacing for radio transmitters.

End of changes to Clause 3.

7. Frame formats

7.3 Management frame body components

7.3.2 Information elements

7.3.2.12 Country information element

Replace Figure 42a with the following:

Element ID	Length
Country String (Octets 1, 2)	
Country String (Octet 3)	First Channel Number/ Regulatory Extension Identifier
Number of Channels/ Regulatory Class	Maximum Transmit Power Level/ Coverage Class
First Channel Number/ Regulatory Extension Identifier	Number of Channels/ Regulatory Class
Maximum Transmit Power Level/ Coverage Class	...
First Channel Number	Number of Channels
Maximum Transmit Power Level	Pad (if needed)

Figure 42a—Country information element

Change the second paragraph of 7.3.2.12 as shown:

The element identifier for this information element shall be 7. The length of the information element is variable, as the element may contain more than one triplet comprising the First Channel Number, Number of Channels, and Maximum Transmit Power Level fields and referred to as subband triplets. Alternatively, where dot11RegulatoryClassesRequired is true and the First Channel Number/Regulatory Extension Identifier octet has a positive integer value of 201 or greater, then that triplet comprises the Regulatory Extension Identifier, Regulatory Class, and Coverage Class fields. Together they are referred to as a regulatory triplet. The minimum length of the information element is 8 octets.

Change the fourth paragraph of 7.3.2.12 as shown:

The First Channel Number/Regulatory Extension Identifier field shall be 1 octet in length. If the field has a positive integer value less than 201, then it shall contain a positive integer value that indicates the lowest channel number in the subband described in this information element. The group of channels described by each pair of the First Channel Number and the Number of Channels fields shall not have overlapping channel identifiers. [For example, the pairs (2,4) and (5,2) overlap and shall not be used together.] The First Channel Number field shall be monotonically increasing where dot11RegulatoryClassesRequired is not true.

Where dot11RegulatoryClassesRequired is true, consecutive subband triplets following a regulatory triplet shall have monotonically increasing First Channel Number fields.

After the sixth paragraph in 7.3.2.12, insert the following text and renumber tables as necessary:

A regulatory class is an index into a set of values for radio equipment sets of rules. The Regulatory Class field shall be 1 octet in length.

A coverage class is an index into a set of values for aAirPropagationTime. The Coverage Class field shall be 1 octet in length.

The Coverage Class field of the regulatory triplet specifies the aAirPropagationTime characteristic used in basic service set (BSS) operation, as shown in Table 20.1a. The characteristic aAirPropagationTime describes variations in actual propagation time that are accounted for in a BSS and, together with maximum transmit power level, allow control of BSS diameter.

Table 20.1a—Coverage Class field parameters

Coverage class value	aAirPropagationTime (μ s)
0	≤ 1
1	3
2	6
3	9
4	12
5	15
6	18
7	21
8	24
9	27
10	30
11	33
12	36
13	39
14	42
15	45
16	48
17	51
18	54
19	57
20	60
21	63
22	66

Table 20.1a—Coverage Class field parameters (continued)

Coverage class value	aAirPropagationTime (μs)
23	69
24	72
25	75
26	78
27	81
28	84
29	87
30	90
31	93
32–255	—

End of changes to Clause 7.

10. Layer management

10.3 Medium access control (MAC) sublayer management entity (MLME) service access point (SAP) interface

10.3.2 Scan

10.3.2.2 MLME-SCAN.confirm

10.3.2.2.2 Semantics of the service primitive

Change the following row in the untitled table defining the primitive parameters in 10.3.2.2.2:

Name	Type	Valid range	Description
ResultCode	Enumeration	SUCCESS, INVALID_PARAMETERS, <u>NOT_SUPPORTED</u>	Indicates the result of the MLME-SCAN.request

10.3.10 Start

10.3.10.2 MLME-START.confirm

10.3.10.2.2 Semantics of the service primitive

Change the following row in the untitled table defining the primitive parameters in 10.3.10.2.2:

Name	Type	Valid range	Description
ResultCode	Enumeration	SUCCESS, INVALID_ PARAMETERS, BSS_ALREADY_ STARTED_OR_ JOINED_NOT_ SUPPORTED	Indicates the result of the MLME- START.request

End of changes to Clause 10.

11. MLME

11.1 Synchronization

11.1.3 Acquiring synchronization, scanning

Insert the following paragraph after the first paragraph in 11.1.3:

Active scanning is prohibited in some frequency bands and regulatory domains. The MAC of a station (STA) receiving an MLME-SCAN.request shall use the regulatory domain information it has to process the request and shall return a result code of NOT_SUPPORTED to a request for an active scan if regulatory domain information indicates an active scan is illegal.

Change the fifth paragraph in 11.1.3 as shown:

If a STA's scanning does not result in finding a BSS with the desired SSID and of the desired type, or does not result in finding any BSS, the STA may start an IBSS upon receipt of the MLME-START.request. The MAC of a STA receiving an MLME-START.request shall use the regulatory domain information it has to process the request and shall return a result code of NOT_SUPPORTED to the request if regulatory domain information indicates starting the BSS is illegal.

End of changes to Clause 11.

17. Orthogonal frequency division multiplexing (OFDM) physical layer (PHY) specification for the 5 GHz band

17.1 Introduction

Change the first paragraph of 17.1 as follows:

This clause specifies the PHY entity for an OFDM system and the additions that have to be made to the base standard to accommodate the OFDM PHY. ~~The radio frequency LAN system is initially aimed for the 5.15–5.25, 5.25–5.35 and 5.725–5.825 GHz unlicensed national information structure (UNII) bands, as regulated in the United States by the Code of Federal Regulations, Title 47, Section 15.407.~~ The OFDM system provides a wireless local area network (WLAN) with data payload communication capabilities of 6, 9, 12, 18, 24, 36, 48, and 54 Mbit/s. The support of transmitting and receiving at data rates of 6, 12, and 24 Mbit/s is mandatory. The system uses 52 subcarriers that are modulated using binary or quadrature phase shift keying (BPSK or QPSK) or using 16- or 64-quadrature amplitude modulation (16-QAM or 64-QAM). Forward error correction coding (convolutional coding) is used with a coding rate of 1/2, 2/3, or 3/4.

Insert the following paragraph at the end of 17.1:

The OFDM system also provides a “half-clocked” operation using 10 MHz channel spacings with data communications capabilities of 3, 4.5, 6, 9, 12, 18, 24, and 27 Mbit/s. The support of transmitting and receiving at data rates of 3, 6, and 12 Mbit/s is mandatory when using 10 MHz channel spacing. The half-clocked operation doubles symbol times and clear channel assessment (CCA) times when using 10 MHz channel spacing. The regulatory requirements and information regarding use of this OFDM system in 4.9 GHz and 5 GHz bands is in Annex I and Annex J.

17.2 OFDM PHY specific service parameter list

17.2.2 TXVECTOR parameters

Change Table 76 as shown:

Table 76—TXVECTOR parameters

Parameter	Associate primitive	Value
LENGTH	PHY-TXSTART.request (TXVECTOR)	1–4095
DATARATE	PHY-TXSTART.request (TXVECTOR)	6, 9, 12, 18, 24, 36, 48, and 54 <u>Mbit/s for 20 MHz channel spacing</u> (Support of 6, 12, and 24 data rates is mandatory.) <u>3, 4.5, 6, 9, 12, 18, 24, and 27 Mbit/s for 10 MHz channel spacing</u> (Support of 3, 6, and 12 data rates is mandatory.)
SERVICE	PHY-TXSTART.request (TXVECTOR)	Scrambler initialization; 7 null bits + 9 reserved null bits
TXPWR_LEVEL	PHY-TXSTART.request (TXVECTOR)	1–8

17.2.2.2 TXVECTOR DATARATE

Change the text in 17.2.2.2 as shown:

The DATARATE parameter describes the bit rate at which the PLCP shall transmit the PSDU. Its value can be any of the rates defined in Table 76. Data rates of 6, 12, and 24 Mbit/s shall be supported for 20 MHz channel spacing, and data rates of 3, 6, and 12 Mbit/s shall be supported for 10 MHz channel spacing; other rates may also be supported.

17.2.3 RXVECTOR parameters

Change Table 77 as shown:

Table 77—RXVECTOR parameters

Parameter	Associate primitive	Value
LENGTH	PHY-RXSTART.indicate	1–4095
RSSI	PHY-RXSTART.indicate (RXVECTOR)	0–RSSI maximum
DATARATE	PHY-RXSTART.request (RXVECTOR)	6, 9, 12, 18, 24, 36, 48, and 54 <u>Mbit/s for</u> <u>20 MHz channel spacing</u> <u>(Support of 6, 12, and 24</u> <u>data rates is mandatory.)</u> 3, 4.5, 6, 9, 12, 18, 24, and 27 <u>Mbit/s for</u> <u>10 MHz channel spacing</u> <u>(Support of 3, 6, and 12</u> <u>data rates is mandatory.)</u>
SERVICE	PHY-RXSTART.request (RXVECTOR)	Null

17.2.3.3 DATARATE

Change the text in 17.2.3.3 as shown:

DATARATE shall represent the data rate at which the current PPDU was received. The allowed values of the DATARATE are 6, 9, 12, 18, 24, 36, 48, or 54 Mbit/s for 20 MHz channel spacing and 3, 4.5, 6, 9, 12, 18, 24, or 27 Mbit/s for 10 MHz channel spacing.

17.3 OFDM physical layer convergence procedure (PLCP) sublayer

17.3.2 PLCP frame format

17.3.2.1 Overview of the PLCP protocol data unit (PPDU) encoding process

Change item b) in 17.3.2.1 as shown:

- b) Produce the PLCP header field from the RATE, LENGTH, and SERVICE fields of the TXVECTOR by filling the appropriate bit fields. The RATE and LENGTH fields of the PLCP header are encoded by a convolutional code at a rate of $R = 1/2$ and are subsequently mapped onto a single BPSK encoded OFDM symbol, denoted as the SIGNAL symbol. In order to facilitate a reliable and timely detection of the RATE and LENGTH fields, 6 zero tail bits are inserted into the PLCP header. The encoding of the SIGNAL field into an OFDM symbol follows the same steps for convolutional encoding, interleaving, BPSK modulation, pilot insertion, Fourier transform, and prepending a guard interval (GI) as described subsequently for data transmission with BPSK-OFDM modulated at 6 Mbit/s coding rate 1/2. The contents of the SIGNAL field are not scrambled. Refer to 17.3.4 for details.

Change the title of 17.3.2.2 as shown:

17.3.2.2 ModulationRate-dependent parameters

Change Table 78 as shown:

Table 78—ModulationRate-dependent parameters

<u>Data rate</u> (Mbit/s)	Modulation	Coding rate (R)	Coded bits per subcarrier (N_{BPSK})	Coded bits per OFDM symbol (N_{CBPS})	Data bits per OFDM symbol (N_{DBPS})	<u>Data rate</u> (Mbit/s) (20 MHz channel spacing)	<u>Data rate</u> (Mbit/s) (10 MHz channel spacing)
6	BPSK	1/2	1	48	24	<u>6</u>	<u>3</u>
9	BPSK	3/4	1	48	36	<u>9</u>	<u>4.5</u>
12	QPSK	1/2	2	96	48	<u>12</u>	<u>6</u>
18	QPSK	3/4	2	96	72	<u>18</u>	<u>9</u>
24	16-QAM	1/2	4	192	96	<u>24</u>	<u>12</u>
36	16-QAM	3/4	4	192	144	<u>36</u>	<u>18</u>
48	64-QAM	2/3	6	288	192	<u>48</u>	<u>24</u>
54	64-QAM	3/4	6	288	216	<u>54</u>	<u>27</u>

17.3.2.3 Timing-related parameters*Change Table 79 as shown:***Table 79—Timing-related parameters**

Parameter	Value (20 MHz channel spacing)	Value (10 MHz channel spacing)
N_{SD} : Number of data subcarriers	48	<u>48</u>
N_{SP} : Number of pilot subcarriers	4	<u>4</u>
N_{ST} : Number of subcarriers, total	$52 (N_{SD} + N_{SP})$	<u>$52 (N_{SD} + N_{SP})$</u>
Δ_F : Subcarrier frequency spacing	0.3125 MHz (= 20 MHz/64)	<u>0.15625 MHz (= 10 MHz/64)</u>
T_{FFT} : Inverse Fast Fourier Transform (IFFT)/ Fast Fourier Transform (FFT) period	$3.2 \mu\text{s} (1/\Delta_F)$	<u>$6.4 \mu\text{s} (1/\Delta_F)$</u>
$T_{PREAMBLE}$: PLCP preamble duration	$16 \mu\text{s} (T_{SHORT} + T_{LONG})$	<u>$32 \mu\text{s} (T_{SHORT} + T_{LONG})$</u>
T_{SIGNAL} : Duration of the SIGNAL BPSK- OFDM symbol	$4.0 \mu\text{s} (T_{GI} + T_{FFT})$	<u>$8.0 \mu\text{s} (T_{GI} + T_{FFT})$</u>
T_{GI} : GI duration	$0.8 \mu\text{s} (T_{FFT}/4)$	<u>$1.6 \mu\text{s} (T_{FFT}/4)$</u>
T_{GI2} : Training symbol GI duration	$1.6 \mu\text{s} (T_{FFT}/2)$	<u>$3.2 \mu\text{s} (T_{FFT}/2)$</u>
T_{SYM} : Symbol interval	$4 \mu\text{s} (T_{GI} + T_{FFT})$	<u>$8 \mu\text{s} (T_{GI} + T_{FFT})$</u>
T_{SHORT} : Short training sequence duration	$8 \mu\text{s} (10 \times T_{FFT}/4)$	<u>$16 \mu\text{s} (10 \times T_{FFT}/4)$</u>
T_{LONG} : Long training sequence duration	$8 \mu\text{s} (T_{GI2} + 2 \times T_{FFT})$	<u>$16 \mu\text{s} (T_{GI2} + 2 \times T_{FFT})$</u>

17.3.2.4 Mathematical conventions in the signal descriptions*Change the third paragraph of 17.3.2.4 as shown:*

The subframes of which Equation (2) are composed are described in 17.3.3, 17.3.4, and 17.3.5.9. The time offsets $t_{SUBFRAME}$ determine the starting time of the corresponding subframe; t_{SIGNAL} is equal to $16 \mu\text{s}$ for 20 MHz channel spacing and $32 \mu\text{s}$ for 10 MHz channel spacing, and t_{DATA} is equal to $20 \mu\text{s}$ for 20 MHz channel spacing and $40 \mu\text{s}$ for 10 MHz channel spacing.

17.3.3 PLCP preamble (SYNC)*Change the first paragraph of 17.3.3 as shown:*

The PLCP Preamble field is used for synchronization. It consists of 10 short symbols and two long symbols that are shown in Figure 110 and described in this subclause. The timings described in this subclause and shown in Figure 110 are for 20 MHz channel spacing and are doubled for half-clocked (i.e., 10 MHz) channel spacing.

17.3.4 Signal field (SIGNAL)

Change the first paragraph of 17.3.4 as shown:

The OFDM training symbols shall be followed by the SIGNAL field, which contains the RATE and the LENGTH fields of the TXVECTOR. The RATE field conveys information about the type of modulation and the coding rate as used in the rest of the packet. The encoding of the SIGNAL single OFDM symbol shall be performed with BPSK modulation of the subcarriers and using convolutional coding at $R = 1/2$. The encoding procedure, which includes convolutional encoding, interleaving, modulation mapping processes, pilot insertion, and OFDM modulation, follows the steps described in 17.3.5.5, 17.3.5.6, and 17.3.5.8, as used for transmission of data at a 6 Mbit/s rate with BPSK-OFDM modulated at coding rate 1/2. The contents of the SIGNAL field are not scrambled.

17.3.4.1 Data rate

Change Table 80 as shown:

Table 80—Contents of the SIGNAL field

Rate (Mbit/s)	R1–R4	<u>Rate (Mbit/s)</u> <u>(20 MHz channel spacing)</u>	<u>Rate (Mbit/s)</u> <u>(10 MHz channel spacing)</u>
6	1101	<u>6</u>	<u>3</u>
9	1111	<u>9</u>	<u>4.5</u>
12	0101	<u>12</u>	<u>6</u>
18	0111	<u>18</u>	<u>9</u>
24	1001	<u>24</u>	<u>12</u>
36	1011	<u>36</u>	<u>18</u>
48	0001	<u>48</u>	<u>24</u>
54	0011	<u>54</u>	<u>27</u>

17.3.7 PLCP data modulation and modulation rate change

Change the text of 17.3.7 as shown:

The PLCP preamble shall be transmitted using an OFDM modulated fixed waveform. The IEEE 802.11 SIGNAL field, BPSK-OFDM modulated at 6 Mbit/s with coding rate 1/2, shall indicate the modulation and coding rate that shall be used to transmit the MPDU. The transmitter (receiver) shall initiate the modulation (demodulation) constellation and the coding rate according to the RATE indicated in the SIGNAL field. The MPDU transmission rate shall be set by the DATARATE parameter in the TXVECTOR, issued with the PHY-TXSTART.request primitive described in 17.2.2.

17.3.8 Physical medium dependent (PMD) operating specifications (general)**17.3.8.1 Outline description**

Change Table 86 as shown:

Table 86—Major parameters of the OFDM PHY

Information data rate	6, 9, 12, 18, 24, 36, 48, and 54 Mbit/s (6, 12, and 24 Mbit/s are mandatory) (20 MHz channel spacing)	<u>3, 4.5, 6, 9, 12, 18, 24, and 27 Mbit/s</u> (<u>3, 6, and 12 Mbit/s are mandatory</u>) (10 MHz channel spacing)
Modulation	BPSK OFDM, QPSK OFDM, 16-QAM OFDM, 64-QAM OFDM	<u>BPSK OFDM, QPSK OFDM,</u> <u>16-QAM OFDM, 64-QAM OFDM</u>
Error correcting code	K = 7 (64 states) convolutional code	<u>K = 7 (64 states) convolutional code</u>
Coding rate	1/2, 2/3, 3/4	<u>1/2, 2/3, 3/4</u>
Number of subcarriers	52	<u>52</u>
OFDM symbol duration	4.0 μ s	<u>8.0 μs</u>
GI ^a	0.8 μ s (T_{GI})	<u>1.6 μs (T_{GI})</u>
Occupied bandwidth	16.6 MHz	<u>8.3 MHz</u>

^aRefer to 17.3.2.4.

17.3.8.2 Regulatory requirements

Change the text of 17.3.8.2 as shown, including the deletion of Table 87, and renumber tables as necessary:

WLANs implemented in accordance with this standard are subject to equipment certification and operating requirements established by regional and national regulatory administrations. The PMD specification establishes minimum technical requirements for interoperability, based upon established regulations at the time this standard was issued. These regulations are subject to revision or may be superseded. Requirements that are subject to local geographic regulations are annotated within the PMD specification. Regulatory requirements that do not affect interoperability are not addressed in this standard. Implementers are referred to the regulatory sources in ~~Table 87~~ Annex I for further information. Operation in countries within defined regulatory domains may be subject to additional or alternative national regulations.

The documents listed in ~~Table 87~~ specify the current regulatory requirements for various geographic areas at the time this standard was developed. They are provided for information only, and are subject to change or revision at any time.

Table 87—Regulatory requirement list

Geographic area	Approval standards	Documents	Approval authority
United States	Federal Communications Commission (FCC)	CFR47 [B7], Part 15, Sections 15.205, 15.209, and 15.247; and Subpart E, Sections 15.401–15.407	FCC
Japan	Ministry of Public Management, Home Affairs, Post and Telecommunications (MPHPT)	MPHPT Ordinance for Regulating Radio Equipment, Article 49–20	MPHPT

17.3.8.3 Operating channel frequencies

17.3.8.3.1 Operating frequency range

Change the first paragraph of 17.3.8.3.1 as shown:

The OFDM PHY shall operate in the 5 GHz band, as allocated by a regulatory body in its operational region. Spectrum allocation in the 5 GHz band is subject to authorities responsible for geographic-specific regulatory domains (e.g., global, regional, and national). The particular channelization to be used for this standard is dependent on such allocation, as well as the associated regulations for use of the allocations. These regulations are subject to revision, or may be superseded. ~~In the United States, the FCC is the agency responsible for the allocation of the 5 GHz U-NII bands.~~

17.3.8.3.2 Channel numbering

Change the text of 17.3.8.3.2 as follows:

Channel center frequencies are defined at every integral multiple of 5 MHz above ~~5 GHz~~Channel starting frequency. The relationship between center frequency and channel number is given by Equation (27):

$$\text{Channel center frequency} = \text{5000 Channel starting frequency} + (n_{ch} \times 5) \text{ (MHz)} \quad (27)$$

where

n_{ch} is 0, 1, ... 200,

Channel starting frequency is defined as `dot11ChannelStartingFactor` × 500 kHz or is defined as 5 GHz for systems where `dot11RegulatoryClassesRequired` is false or not defined.

For example, `dot11ChannelStartingFactor` = 10 000 indicates that Channel zero center frequency is 5.000 GHz. The value NULL for n_{ch} shall be reserved, and a channel center frequency of 5.000 GHz shall be indicated by `dot11ChannelStartingFactor` = 8000 and n_{ch} = 200. An SME managing multiple channel sets can change the channel set being managed by changing the value of `dot11ChannelStartingFactor`.

This definition provides a unique numbering system for all channels with 5 MHz spacing ~~from 5 GHz to 6 GHz~~, as well as the flexibility to define channelization sets for all current and future regulatory domains.

17.3.8.3.3 Channelization

Change the text of 17.3.8.3.3 as shown, including the deletion of Table 88 and Figure 119, and renumber tables and figures as necessary:

The set of ~~valid~~ operating channel numbers by regulatory domain is defined in ~~Table 88–Annex J~~. As shown in Figure 117, no subcarrier is allocated on the channel center frequency.

~~**Table 88—Valid operating channel numbers by regulatory domain and band**~~

Regulatory domain	Band (GHz)	Operating channel numbers	Channel center frequencies (MHz)
United States CEPT	U-NII lower band (5.15–5.25)	36 40 44 48	5180 5200 5220 5240
United States CEPT	U-NII middle band (5.25–5.35)	52 56 60 64	5260 5280 5300 5320
CEPT	(5.47–5.725)	100 104 108 112 116 120 124 128 132 136 140	5500 5520 5540 5560 5580 5600 5620 5640 5660 5680 5700
United States	U-NII upper band (5.725–5.825)	149 153 157 161	5745 5765 5785 5805

The OFDM PHY shall operate in the 5 GHz band, as allocated by a regulatory body in its operational region.

The center frequency is indicated in Figure 119 for the US frequency channel plan; however, no subcarrier is allocated on the center frequency as described in Figure 117.

In a multiple cell network topology, overlapping and/or adjacent cells using different channels can operate simultaneously.




Figure 43—OFDM PHY frequency channel plan for the United States

17.3.8.4 Transmit and receive in-band and out-of-band spurious emissions

Change the text of 17.3.8.4 as shown:

The OFDM PHY shall conform to in-band and out-of-band spurious emissions as set by regulatory bodies. ~~For the United States, refer to FCC 15.407.~~

17.3.8.6 Slot time

Change the text of 17.3.8.6 as follows:

The slot time for the OFDM PHY shall be $9\ \mu\text{s}$ for 20 MHz channel spacing, ~~which is the sum of the RX-to-TX turnaround time, MAC processing delay, and CCA detect time ($< 4\ \mu\text{s}$)~~ and shall be $13\ \mu\text{s}$ for 10 MHz channel spacing. ~~The propagation delay shall be regarded as being included in the CCA detect time.~~

~~Where dot11RegulatoryClassesRequired is true, the value of the slot time shall be increased by the value of $3\ \mu\text{s} \times \text{coverage class}$. The default value of coverage class shall be zero.~~

~~NOTE—Distributed coordination function (DCF) operation over larger BSS diameters is facilitated by relaxing some PHY timing parameters, while maintaining compatibility with existing implementations in small BSS diameters.¹~~

17.3.9 PMD transmit specifications

17.3.9.1 Transmit power levels

Change the text of 17.3.9.1 as shown, including the deletion of Table 89, and renumber tables as necessary:

The maximum allowable ~~transmit output~~ power by regulatory domain is ~~shown in Table 89~~ defined in Annex I.

¹Notes in text, tables, and figures are given for information only and do not contain requirements needed to implement the standard.

Table 89—Transmit power levels by regulatory domain

Frequency band (GHz)	United States (Maximum output power with up to 6 dBi antenna gain) (mW)	CERP (EIRP)
5.15–5.25	40 (2.5 mW/MHz)	200 mW
5.25–5.35	200 (12.5 mW/MHz)	200 mW
5.470–5.725	—	1 W
5.725–5.825	800 (50 mW/MHz)	—

17.3.9.2 Transmit spectrum mask

Change the text of 17.3.9.2 as shown:

For operation using 20 MHz channel spacing, the transmitted spectrum shall have a 0 dBr (dB relative to the maximum spectral density of the signal) bandwidth not exceeding 18 MHz, –20 dBr at 11 MHz frequency offset, –28 dBr at 20 MHz frequency offset, and –40 dBr at 30 MHz frequency offset and above. The transmitted spectral density of the transmitted signal shall fall within the spectral mask, as shown in Figure 120. The measurements shall be made using a 100 kHz resolution bandwidth and a 30 kHz video bandwidth. For operation using 10 MHz channel spacing, the transmitted spectrum shall have a 0 dBr bandwidth not exceeding 9 MHz, –20 dBr at 5.5 MHz frequency offset, –28 dBr at 10 MHz frequency offset, and –40 dBr at 15 MHz frequency offset and above. The transmit spectrum mask by regulatory domain is defined in Annex I and Annex J.

17.3.9.6 Modulation accuracy

17.3.9.6.3 Transmit constellation error

Change Table 90 as shown:

Table 90—Allowed relative constellation error versus data rate

Data rate (Mbit/s)	Relative constellation error (dB)	Modulation	Coding rate (R)
6	–5	BPSK	1/2
9	–8	BPSK	3/4
12	–10	QPSK	1/2
18	–13	QPSK	3/4
24	–16	16-QAM	1/2
36	–19	16-QAM	3/4
48	–22	64-QAM	2/3
54	–25	64-QAM	3/4

17.3.10 PMD receiver specifications

Change the title of 17.3.10.1 as shown:

17.3.10.1 Receiver minimum input level sensitivity

Change Table 91 as shown:

Table 91—Receiver performance requirements

<u>Modulation</u>	<u>Coding rate (R)</u>	<u>Data rate (Mbit/s)</u>	<u>Minimum sensitivity (dBm)</u>	<u>Adjacent channel rejection (dB)</u>	<u>Alternate adjacent channel rejection (dB)</u>	<u>Minimum sensitivity (dBm) (20 MHz channel spacing)</u>	<u>Minimum sensitivity (dBm) (10 MHz channel spacing)</u>
<u>BPSK</u>	<u>1/2</u>	<u>6</u>	<u>-82</u>	<u>16</u>	<u>32</u>	<u>-82</u>	<u>-85</u>
<u>BPSK</u>	<u>3/4</u>	<u>9</u>	<u>-81</u>	<u>15</u>	<u>31</u>	<u>-81</u>	<u>-84</u>
<u>QPSK</u>	<u>1/2</u>	<u>12</u>	<u>-79</u>	<u>13</u>	<u>29</u>	<u>-79</u>	<u>-82</u>
<u>QPSK</u>	<u>3/4</u>	<u>18</u>	<u>-77</u>	<u>11</u>	<u>27</u>	<u>-77</u>	<u>-80</u>
<u>16-QAM</u>	<u>1/2</u>	<u>24</u>	<u>-74</u>	<u>8</u>	<u>24</u>	<u>-74</u>	<u>-77</u>
<u>16-QAM</u>	<u>3/4</u>	<u>36</u>	<u>-70</u>	<u>4</u>	<u>20</u>	<u>-70</u>	<u>-73</u>
<u>64-QAM</u>	<u>2/3</u>	<u>48</u>	<u>-66</u>	<u>0</u>	<u>16</u>	<u>-66</u>	<u>-69</u>
<u>64-QAM</u>	<u>3/4</u>	<u>54</u>	<u>-65</u>	<u>-1</u>	<u>15</u>	<u>-65</u>	<u>-68</u>

17.3.10.5 CCA sensitivity

Change the text of 17.3.10.5 as shown:

The start of a valid OFDM transmission at a receive level equal to or greater than the minimum ~~6 Mbit/s modulation and coding rate sensitivity~~ (-82 dBm for 20 MHz channel spacing and -85 dBm for 10 MHz channel spacing) shall cause CCA to indicate busy with a probability > 90% within 4 μ s for 20 MHz channel spacing and 8 μ s for 10 MHz channel spacing. If the preamble portion was missed, the receiver shall hold the carrier sense (CS) signal busy for any signal 20 dB above the minimum ~~6 Mbit/s modulation and coding rate sensitivity~~ (-62 dBm for 20 MHz channel spacing and -65 dBm for 10 MHz channel spacing).

NOTE—CCA detect time is based on finding the short sequences in the preamble, so when T_{SYM} doubles, so does CCA detect time.

17.4 OFDM PLME

17.4.2 OFDM PHY MIB

Change Table 92 as shown (only affected rows are given here):

Table 92—MIB attribute default values/ranges

Managed object	Default value/range	Operational semantics
dot11 PHY Operation Table		
dot11 Current reg domain	Implementation dependent	Static <u>Dynamic</u>
dot11 Supported Data Rates Tx Table		
dot11 Supported data -rates Tx value	6, 9, 12, 18, 24, 36, 48, and 54 Mbit/s <u>for 20 MHz channel spacing</u> (Mandatory rates: 6, 12, and 24) 3, 4.5, 6, 9, 12, 18, 24, and 27 Mbit/s <u>for 10 MHz channel spacing</u> (Mandatory rates: 3, 6, and 12)	Static
dot11 Supported Data Rates Rx Table		
dot11 Supported data -rates Rx value	6, 9, 12, 18, 24, 36, 48, and 54 Mbit/s <u>for 20 MHz channel spacing</u> (Mandatory rates: 6, 12, and 24) 3, 4.5, 6, 9, 12, 18, 24, and 27 Mbit/s <u>for 10 MHz channel spacing</u> (Mandatory rates: 3, 6, and 12)	Static
dot11 PHY OFDM Table		
dot11 Channel starting factor	Implementation dependent	<u>Dynamic</u>

17.4.3 OFDM TXTIME calculation

Change the last paragraph in 17.4.3 as shown:

Equation (30) does not include the effect of rounding to the next OFDM symbol and may be in error by $\pm 2 \mu s T_{SYM}/2$.

17.4.4 OFDM PHY characteristics

Change Table 93 as shown:

Table 93—OFDM PHY characteristics

Characteristics	Value (20 MHz channel spacing)	Value (10 MHz channel spacing)
aSlotTime	9 μ s	<u>13 μs</u>
aSIFSTime	16 μ s	<u>32 μs</u>
aCCATime	< 4 μ s	<u>< 8 μs</u>
aRxTxTurnaroundTime	< 2 μ s	<u>< 2 μs</u>
aTxPLCPDelay	Implementation dependent	<u>Implementation dependent</u>
aRxPLCPDelay	Implementation dependent	<u>Implementation dependent</u>
aRxTxSwitchTime	<< 1 μ s	<u><< 1 μs</u>
aTxRampOnTime	Implementation dependent	<u>Implementation dependent</u>
aTxRampOffTime	Implementation dependent	<u>Implementation dependent</u>
aTxRFDelay	Implementation dependent	<u>Implementation dependent</u>
aRxRFDelay	Implementation dependent	<u>Implementation dependent</u>
aAirPropagationTime	<< 1 μ s	<u><< 1 μs</u>
aMACProcessingDelay	< 2 μ s	<u>< 2 μs</u>
aPreambleLength	20 μ s	<u>40 μs</u>
aPLCPHeaderLength	4 μ s	<u>8 μs</u>
aMPDUMaxLength	4095	<u>4095</u>
aCWmin	15	<u>15</u>
aCWmax	1023	<u>1023</u>

17.5 OFDM PMD sublayer

17.5.4 Basic service and options

17.5.4.3 PMD_SAP service primitive parameters

Change Table 96 as shown:

Table 96—List of parameters for the PMD primitives

Parameter	Associate primitive	Value (20 MHz channel spacing)	Value (10 MHz channel spacing)
TXD_UNIT	PMD_DATA.request	One(1), Zero(0): one OFDM symbol value	<u>One(1), Zero(0): one OFDM symbol value</u>
RXD_UNIT	PMD_DATA.indicate	One(1), Zero(0): one OFDM symbol value	<u>One(1), Zero(0): one OFDM symbol value</u>
TXPWR_LEVEL	PMD_TXPWRLVL.request	1–8 (max of 8 levels)	<u>1–8 (max of 8 levels)</u>

Table 96—List of parameters for the PMD primitives (continued)

Parameter	Associate primitive	Value <u>(20 MHz channel spacing)</u>	Value <u>(10 MHz channel spacing)</u>
RATE	PMD_RATE.request	12 Mbit/s (for BPSK) 24 Mbit/s (for QPSK) 48 Mbit/s (for 16-QAM) 72 Mbit/s (for 64-QAM)	<u>6 Mbit/s (for BPSK)</u> <u>12 Mbit/s (for QPSK)</u> <u>24 Mbit/s (for 16-QAM)</u> <u>36 Mbit/s (for 64-QAM)</u>
RSSI	PMD_RSSI.indicate	0–8 bits of RSSI	<u>0–8 bits of RSSI</u>

End of changes to Clause 17.

Annex A

(normative)

Protocol Implementation Conformance Statements (PICS)

Change the title of A.4 as shown:

A.4 PICS proforma—IEEE Std 802.11, 1999 Edition (Reaff 2003)

Insert the following row at the end of the table in A.4.3:

A.4.3 Implementation under test (IUT) configuration

Item	IUT configuration	References	Status	Support
*CF11	Is regulatory classes capability implemented?	7.3.2.12, 17.3.8.3.2, 17.3.8.6, 17.4.2, Annex I, Annex J	CF6&CF8& CF10:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>

Insert the following rows in numerical order into the table in A.4.8 (the existing table section titles have been included here to clarify where to insert the new rows):

A.4.8 Orthogonal frequency division multiplex (OFDM) physical layer (PHY) functions

Item	Feature	References	Status	Support
OF1: OFDM PHY Specific Service Parameters				
*OF1.7	10 MHz Channel spacing	17.2.2, 17.2.3, 17.2.3.3	CF11:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF1.7.1	DATARATE = 3 Mbit/s (10 MHz channel spacing)	17.2.2, 17.2.3, 17.2.3.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF1.7.2	DATARATE = 4.5 Mbit/s (10 MHz channel spacing)	17.2.2, 17.2.3, 17.2.3.3	CF11& OF1.7:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF1.7.3	DATARATE = 6 Mbit/s (10 MHz channel spacing)	17.2.2, 17.2.3, 17.2.3.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF1.7.4	DATARATE = 9 Mbit/s (10 MHz channel spacing)	17.2.2, 17.2.3, 17.2.3.3	CF11& OF1.7:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF1.7.5	DATARATE = 12 Mbit/s (10 MHz channel spacing)	17.2.2, 17.2.3, 17.2.3.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>

A.4.8 Orthogonal frequency division multiplex (OFDM) physical layer (PHY) functions *(continued)*

Item	Feature	References	Status	Support
OF1.7.6	DATARATE = 18 Mbit/s (10 MHz channel spacing)	17.2.2, 17.2.3, 17.2.3.3	CF11& OF1.7:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF1.7.7	DATARATE = 24 Mbit/s (10 MHz channel spacing)	17.2.2, 17.2.3, 17.2.3.3	CF11& OF1.7:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF1.7.8	DATARATE = 27 Mbit/s (10 MHz channel spacing)	17.2.2, 17.2.3, 17.2.3.3	CF11& OF1.7:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF2: OFDM PLCP Sublayer				
OF2.21	Modulation-dependent parameters (10 MHz channel spacing)	17.3.2.2	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF2.22	Timing-related parameters (10 MHz channel spacing)	17.3.2.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF2.23	PLCP header: RATE (10 MHz channel spacing)	17.3.4.1	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3: PDM Operating Specification General				
OF3.11	Occupied channel bandwidth (10 MHz channel spacing)	17.3.8.1	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
*OF3.12	Operating frequency range	17.3.8.2	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.12.1	4.9 GHz band	Annex J	CF11:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.12.2	5.0 GHz band	Annex J	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.12.3	5.47–5.725 GHz band in Europe	Annex J	CF10& CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.13	Channelization	17.3.8.3.3, J.2.1	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.13.1	4.9 GHz band (20 MHz channel spacing)	17.3.8.3.3	CF11& OF3.12.1: M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.13.2	4.9 GHz band (10 MHz channel spacing)	17.3.8.3.3	CF11& OF3.12.1& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.13.3	5.0 GHz band (20 MHz channel spacing)	17.3.8.3.3	CF11& OF3.12.2: M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.13.4	5.0 GHz band (10 MHz channel spacing)	17.3.8.3.3	CF11& OF3.12.2& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.13.5	5.15–5.25 GHz band in Japan	17.3.8.3.3	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.13.6	5.47–5.725 GHz in Europe	17.3.8.3.3	CF11& OF3.12.3: M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.14	Number of operating channels	17.3.8.3.3	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>

A.4.8 Orthogonal frequency division multiplex (OFDM) physical layer (PHY) functions (continued)

Item	Feature	References	Status	Support
OF3.15	Operating channel frequencies	17.3.8.3.3	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.16	Transmit and receive in-band and out-of-band spurious emissions (nomadic use)	17.3.8.4	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.16.1	Interference-limited areas, 4.9 GHz band (20 MHz channel spacing)	17.3.8.4	CF11& OF3.12.1: M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.16.2	Interference-limited areas, 4.9 GHz band (10 MHz channel spacing)	17.3.8.4	CF11& OF3.12.1& OF1.7:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.16.3	Interference-limited areas, 5.0 GHz band (20 MHz channel spacing)	17.3.8.4	CF11& OF3.12.2: M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.16.4	Interference-limited areas, 5.0 GHz band (10 MHz channel spacing)	17.3.8.4	CF11& OF3.12.2& OF1.7:O	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.17	Slot time (20 MHz channel spacing and regulatory classes)	17.3.8.6	CF11& RC2:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF3.18	Slot time (10 MHz channel spacing and regulatory classes)	17.3.8.6	CF11& RC3& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4: PMD Transmit Specification				
OF4.7	Power level, 4.9 GHz band (20 MHz channel spacing)	17.3.9.1	CF11& OF3.12.1: M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.8	Power level, 5.0 GHz band (20 MHz channel spacing)	17.3.9.1	CF11& OF3.12.2: M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.9	Power level, 5.47–5.725 GHz band in Europe	17.3.9.1	CF11& OF3.12.3: M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.10	Power level, 4.9 GHz band (10 MHz channel spacing)	17.3.9.1	CF11& OF3.12.1& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.11	Power level, 5.0 GHz band (10 MHz channel spacing)	17.3.9.1	CF11& OF3.12.2& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.12	Spectrum mask (20 MHz channel spacing)	17.3.9.2	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.13	Spectrum mask (10 MHz channel spacing)	17.3.9.2	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.14	Transmitter constellation error (10 MHz channel spacing)			
OF4.14.1	Transmitter constellation error < -5 dB (10 MHz channel spacing)	17.3.9.6.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.14.2	Transmitter constellation error < -8 dB (10 MHz channel spacing)	17.3.9.6.3	CF11& OF1.7.2:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>

A.4.8 Orthogonal frequency division multiplex (OFDM) physical layer (PHY) functions *(continued)*

Item	Feature	References	Status	Support
OF4.14.3	Transmitter constellation error < -10 dB (10 MHz channel spacing)	17.3.9.6.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.14.4	Transmitter constellation error < -13 dB (10 MHz channel spacing)	17.3.9.6.3	CF11& OF1.7.4:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.14.5	Transmitter constellation error < -16 dB (10 MHz channel spacing)	17.3.9.6.3	CF11& OF1.7.5:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.14.6	Transmitter constellation error < -19 dB (10 MHz channel spacing)	17.3.9.6.3	CF11& OF1.7.6:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.14.7	Transmitter constellation error < -22 dB (10 MHz channel spacing)	17.3.9.6.3	CF11& OF1.7.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF4.14.8	Transmitter constellation error < -25 dB (10 MHz channel spacing)	17.3.9.6.3	CF11& OF1.7.8:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5: PMD Receiver Specifications				
OF5.6	Maximum input level sensitivity at packet error rate (PER) = 10% with 1000 octet frames (10 MHz channel spacing)			
OF5.6.1	-85 dBm for 3 Mbit/s (10 MHz channel spacing)	17.3.10.1	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.6.2	-84 dBm for 4.5 Mbit/s (10 MHz channel spacing)	17.3.10.1	CF11& OF1.7.2:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.6.3	-82 dBm for 6 Mbit/s (10 MHz channel spacing)	17.3.10.1	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.6.4	-80 dBm for 9 Mbit/s (10 MHz channel spacing)	17.3.10.1	CF11& OF1.7.4:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.6.5	-77 dBm for 12 Mbit/s (10 MHz channel spacing)	17.3.10.1	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.6.6	-73 dBm for 18 Mbit/s (10 MHz channel spacing)	17.3.10.1	CF11& OF1.7.6:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.6.7	-69 dBm for 24 Mbit/s (10 MHz channel spacing)	17.3.10.1	CF11& OF1.7.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.6.8	-68 dBm for 27 Mbit/s (10 MHz channel spacing)	17.3.10.1	CF11& OF1.7.8:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.7	Adjacent channel rejection (10 MHz channel spacing)	17.3.10.2	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.8	Nonadjacent channel rejection (10 MHz channel spacing)	17.3.10.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.9	Maximum input level (10 MHz channel spacing)	17.3.10.4	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF5.10	CCA sensitivity (10 MHz channel spacing)	17.3.10.5	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF8: PLME				
OF8.4	PLME:support PHY characteristics (dot11ChannelStartingFactor)	17.4.2	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>

A.4.8 Orthogonal frequency division multiplex (OFDM) physical layer (PHY) functions (continued)

Item	Feature	References	Status	Support
OF9: OFDM PMD Sublayer				
OF9.4				
OF9.4.1	Parameter: RATE (6 Mbit/s for 10 MHz channel spacing)	17.5.4.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF9.4.2	Parameter: RATE (12 Mbit/s for 10 MHz channel spacing)	17.5.4.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF9.4.3	Parameter: RATE (24 Mbit/s for 10 MHz channel spacing)	17.5.4.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF9.4.4	Parameter: RATE (36 Mbit/s for 10 MHz channel spacing)	17.5.4.3	CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
OF10: Geographic Area Specific Requirements				
OF10.2				
	Regulatory domain extensions	17.3.8.3.3, 17.3.8.4, 17.3.9.1 17.3.9.2, Annex J	CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>

Insert the following row at the end of the table in A.4.10:

A.4.10 Regulatory domain extensions

Item	Protocol capability	References	Status	Support
MD12	Regulatory and Coverage classes	7.3.2.12	RC1:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>

After A.4.12, insert A.4.13:

A.4.13 Regulatory classes extensions

Item	Protocol capability	References	Status	Support
RC1	Regulatory and Coverage classes	7.3.2.12	CF8&CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
RC2	Regulatory and Coverage classes (20 MHz channel spacing)	7.3.2.12, 17.3.8.6	CF8&CF11:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>
RC3	Regulatory and Coverage classes (10 MHz channel spacing)	7.3.2.12, 17.3.8.6	CF8&CF11& OF1.7:M	Yes <input type="checkbox"/> No <input type="checkbox"/> N/A <input type="checkbox"/>

Annex D

(normative)

ASN.1 encoding of the MAC and PHY MIB

In “Major sections” of Annex D, add the following text at the end of the Station Management attributes:

```

-- dot11smt GROUPS
-- dot11StationConfigTable ::= { dot11smt 1 }
-- dot11AuthenticationAlgorithmsTable ::= { dot11smt 2 }
-- dot11WEPEDefaultKeysTable ::= { dot11smt 3 }
-- dot11WEPKeyMappingsTable ::= { dot11smt 4 }
-- dot11PrivacyTable ::= { dot11smt 5 }
-- dot11SMTnotification ::= { dot11smt 6 }
-- dot11MultiDomainCapabilityTable ::= { dot11smt 7 }
-- dot11SpectrumManagementTable ::= { dot11smt 8 }
-- dot11RSNAConfigTable ::= { dot11smt 9 }
-- dot11RSNAConfigPairwiseCiphersTable ::= { dot11smt 10 }
-- dot11RSNAConfigAuthenticationSuitesTable ::= { dot11smt 11 }
-- dot11RSNAStatsTable ::= { dot11smt 12 }
-- dot11RegulatoryClassesTable ::= { dot11smt 13 }

```

In “SMT Station Config Table” in Annex D, change Dot11StationConfigEntry as follows:

```

Dot11StationConfigEntry ::=
SEQUENCE {
    dot11StationID                MacAddress,
    dot11MediumOccupancyLimit     INTEGER,
    dot11CFPollable               TruthValue,
    dot11CFPPeriod                INTEGER,
    dot11CFPMaxDuration           INTEGER,
    dot11AuthenticationResponseTimeout Unsigned32,
    dot11PrivacyOptionImplemented TruthValue,
    dot11PowerManagementMode      INTEGER,
    dot11DesiredSSID              OCTET STRING,
    dot11DesiredBSSType           INTEGER,
    dot11OperationalRateSet       OCTET STRING,
    dot11BeaconPeriod             INTEGER,
    dot11DTIMPeriod              INTEGER,
    dot11AssociationResponseTimeout Unsigned32,
    dot11DisassociateReason       INTEGER,
    dot11DisassociateStation      MacAddress,
    dot11DeauthenticateReason     INTEGER,
    dot11DeauthenticateStation    MacAddress,
    dot11AuthenticateFailStatus   INTEGER,
    dot11AuthenticateFailStation  MacAddress,
    dot11MultiDomainCapabilityImplemented TruthValue,
    dot11MultiDomainCapabilityEnabled TruthValue,
    dot11CountryString            OCTET STRING,
    dot11SpectrumManagementImplemented TruthValue,
    dot11SpectrumManagementRequired TruthValue,
    dot11RSNAOptionImplemented    TruthValue,
    dot11RSNAPreauthenticationImplemented TruthValue,
    dot11RegulatoryClassesImplemented TruthValue,
    dot11RegulatoryClassesRequired TruthValue }

```

In “SMT Station Config Table” in Annex D, insert the following attributes after dot11RSNA-PreauthenticationImplemented { dot11StationConfigEntry 27 }:

```
dot11RegulatoryClassesImplemented OBJECT-TYPE
    SYNTAX TruthValue
    MAX-ACCESS read-write
    STATUS current
    DESCRIPTION
        "This attribute, when TRUE, indicates that the station implementa-
        tion is capable of supporting regulatory classes. The capability is
        disabled otherwise. The default value of this attribute is FALSE."
    ::= { dot11StationConfigEntry 28 }

dot11RegulatoryClassesRequired OBJECT-TYPE
    SYNTAX TruthValue
    MAX-ACCESS read-write
    STATUS current
    DESCRIPTION
        "A STA will use the defined regulatory classes procedures if and
        only if this attribute is TRUE. The default value of this attribute
        is FALSE."
    ::= { dot11StationConfigEntry 29 }
```

After the end of the “dot11SpectrumManagement TABLE” in Annex D, insert the following dot11RegulatoryClasses TABLE:

```
-- *****
-- * dot11RegulatoryClasses TABLE
-- *****

dot11RegulatoryClassesTable OBJECT-TYPE
    SYNTAX SEQUENCE OF Dot11RegulatoryClassesEntry
    MAX-ACCESS not-accessible
    STATUS current
    DESCRIPTION
        "(Conceptual) table of attributes for regulatory classes"
    ::= { dot11smt 13}

dot11RegulatoryClassesEntry OBJECT-TYPE
    SYNTAX Dot11RegulatoryClassesEntry
    MAX-ACCESS not-accessible
    STATUS current
    DESCRIPTION
        "An entry (conceptual row) in the Regulatory Classes Table.
        IfIndex - Each 802.11 interface is represented by an ifEntry.
        Interface tables in this MIB are indexed by ifIndex."
    INDEX {ifIndex, dot11RegulatoryClassesIndex}
    ::= { dot11RegulatoryClassesTable 1 }

Dot11RegulatoryClassesEntry ::=
    SEQUENCE {
        dot11RegulatoryClassesIndex      Integer32,
        dot11RegulatoryClass              INTEGER,
        dot11CoverageClass                INTEGER }

dot11RegulatoryClassesIndex OBJECT-TYPE
    SYNTAX Integer32
    MAX-ACCESS not-accessible
    STATUS current
    DESCRIPTION
        "The auxiliary variable used to identify instances of the columnar
        objects in the Regulatory Classes Table."
    ::= { dot11RegulatoryClassesEntry 1 }
```

```

dot11RegulatoryClass OBJECT-TYPE
    SYNTAX INTEGER
    MAX-ACCESS read-write
    STATUS current
    DESCRIPTION
        "This attribute shall indicate the regulatory class to be used. The
        default value of this attribute shall be zero."
    ::= { dot11RegulatoryClassesEntry 2 }

dot11CoverageClass OBJECT-TYPE
    SYNTAX INTEGER
    MAX-ACCESS read-write
    STATUS current
    DESCRIPTION
        "This attribute shall indicate the coverage class to be used. The
        default value of this attribute shall be zero."
    ::= { dot11RegulatoryClassesEntry 3 }

-- *****
-- * End of dot11RegulatoryClasses TABLE
-- *****

```

In “dot11RegDomainsSupported TABLE” in Annex D, change dot11RegDomainsSupportedTable object as shown:

```

dot11RegDomainsSupportedTable OBJECT-TYPE
    SYNTAX SEQUENCE OF Dot11RegDomainsSupportedEntry
    MAX-ACCESS not-accessible
    STATUS current
    DESCRIPTION
        "There are different operational requirements dependent on the
        regulatory domain. This attribute list describes the regulatory
        domains the PLCP and PMD support in this implementation. Currently
        defined values and their corresponding Regulatory Domains are as
        follows:

        FCC (USA) = X'10', DOC (Canada) = X'20', ETSI (most of
        Europe) = X'30', Spain = X'31', France = X'32', MKKMPHPT
        (Japan) = X'40', Other = X'00' "
    ::= { dot11phy 7}

```

In “dot11RegDomainsSupported TABLE” in Annex D, change dot11RegDomainsSupportedValue object as shown:

```

dot11RegDomainsSupportedValue OBJECT-TYPE
    SYNTAX INTEGER { fcc(16), doc(32), etsi(48), spain (49), france(50),
        mkkmpht (64) }
    MAX-ACCESS read-only
    STATUS current
    DESCRIPTION
        "There are different operational requirements dependent on the
        regulatory domain. This attribute list describes the regulatory
        domains the PLCP and PMD support in this implementation. Currently
        defined values and their corresponding Regulatory Domains are as
        follows:

        FCC (USA) = X'10', DOC (Canada) = X'20', ETSI (most of
        Europe) = X'30', Spain = X'31', France = X'32', MKKMPHPT
        (Japan) = X'40' "
    ::= { dot11RegDomainsSupportedEntry 2 }

```


In “dot11PhyOFDM TABLE” in Annex D, change Dot11PhyOFDMEntry as shown:

```
Dot11PhyOFDMEntry ::=
    SEQUENCE { dot11CurrentFrequency          INTEGER,
               dot11TTIThreshold             Integer32,
               dot11FrequencyBandsSupported  INTEGER,
               dot11ChannelStartingFactor    Integer32 }
```

In “dot11PhyOFDM TABLE” in Annex D, change dot11FrequencyBandsSupported object as shown:

```
dot11FrequencyBandsSupported OBJECT-TYPE
    SYNTAX INTEGER (1..127)
    MAX-ACCESS read-only
    STATUS current
    DESCRIPTION
        "The capability of the OFDM PHY implementation to operate in the
        three U-NII bands, in the CEPT Band B, and in the Japanese 5 GHz
        bands. Coded as an integer value of a seven bit field as follows:
        bit 0 .. capable of operating in the lower (5.15-5.25 GHz)
            U-NII band
        bit 1 .. capable of operating in the middle (5.25-5.35 GHz)
            U-NII band
        bit 2 .. capable of operating in the upper (5.725-5.825 GHz)
            U-NII band
        bit 3 .. capable of operating in CEPT Band B (5.47-5.725 GHz)
        bit 4 .. capable of operating in the lower Japanese (5.15-
            5.25 GHz) band
        bit 5 .. capable of operating in the Japanese 5.0 (5.03-
            5.091 GHz) band
        bit 6 .. capable of operating in the Japanese 4.9 (4.9-5.0 GHz)
            band
        For example, for an implementation capable of operating in the
        lower and mid bands, this attribute would take the value 3."
    ::= { dot11PhyOFDMEntry 3 }
```

In “dot11PhyOFDM TABLE” in Annex D, insert the following object after dot11FrequencyBandsSupported { dot11PhyOFDMEntry 3 }:

```
dot11ChannelStartingFactor OBJECT-TYPE
    SYNTAX Integer32 (8000..10000)
    MAX-ACCESS read-write
    STATUS current
    DESCRIPTION
        "The base factor from which channel center frequencies are
        calculated. This number is multiplied by 500 kHz to form the base
        frequency to be added to the channel number x 5 MHz. The default
        value of this attribute shall be 10 000."
    ::= { dot11PhyOFDMEntry 4 }
```

In “Compliance Statements” of Annex D, change OPTIONAL-GROUPS as follows:

```
-- OPTIONAL-GROUPS { dot11SMTprivacy, dot11MACStatistics,
-- dot11PhyAntennaComplianceGroup, dot11PhyTxPowerComplianceGroup,
-- dot11PhyRegDomainsSupportGroup,
-- dot11PhyAntennasListGroup, dot11PhyRateGroup,
-- dot11SMTbase3, dot11MultiDomainCapabilityGroup,
-- dot11PhyFHSSComplianceGroup2, dot11RSNAadditions,
-- dot11RegulatoryClassesGroup }
--
::= { dot11Compliances 1 }
```

In “Groups – units of conformance” of Annex D, change dot11PhyOFDMComplianceGroup object as shown:

```
dot11PhyOFDMComplianceGroup OBJECT-GROUP
  OBJECTS { dot11CurrentFrequency,
            dot11TTThreshold,
            dot11FrequencyBandsSupported, →
            dot11ChannelStartingFactor }
  STATUS current
  DESCRIPTION
    "Attributes that configure the OFDM for IEEE 802.11."
  ::= { dot11Groups 17 }
```

In “Groups - units of conformance” of Annex D, change dot11SMTbase3 as follows:

```
dot11SMTbase3 OBJECT-GROUP
  OBJECTS { dot11MediumOccupancyLimit,
            dot11CFPollable,
            dot11CFPPeriod,
            dot11CFPMaxDuration,
            dot11AuthenticationResponseTimeOut,
            dot11PrivacyOptionImplemented,
            dot11PowerManagementMode,
            dot11DesiredSSID, dot11DesiredBSSType,
            dot11OperationalRateSet,
            dot11BeaconPeriod, dot11DTIMPeriod,
            dot11AssociationResponseTimeOut,
            dot11DisassociateReason,
            dot11DisassociateStation,
            dot11DeauthenticateReason,
            dot11DeauthenticateStation,
            dot11AuthenticateFailStatus,
            dot11AuthenticateFailStation,
            dot11MultiDomainCapabilityImplemented,
            dot11MultiDomainCapabilityEnabled,
            dot11CountryString }
  STATUS current deprecated
  DESCRIPTION
    "The SMTbase3 object class provides the necessary support at the
    STA to manage the processes in the STA so that the STA may work
    cooperatively as a part of an IEEE 802.11 network, when the STA is
    capable of multidomain operation. This object group should be
    implemented when the multidomain capability option is implemented."
  ::= { dot11Groups 20 }
```

In “Groups - units of conformance” in Annex D, insert the following objects after dot11SMTbase4 { dot11Groups 26 }:

```
dot11RegulatoryClassesGroup OBJECT-GROUP
  OBJECTS { dot11RegulatoryClass,
            dot11CoverageClass }
  STATUS current
  DESCRIPTION
    "Attributes that configure the OFDM for IEEE 802.11 in many
    regulatory domains."
  ::= { dot11Groups 29 }
```

```
dot11SMTbase5 OBJECT-GROUP
  OBJECTS { dot11MediumOccupancyLimit,
            dot11CFPollable,
            dot11CFPPeriod,
            dot11CFPMaxDuration,
```

```
dot11AuthenticationResponseTimeOut,  
dot11PrivacyOptionImplemented,  
dot11PowerManagementMode,  
dot11DesiredSSID, dot11DesiredBSSType,  
dot11OperationalRateSet,  
dot11BeaconPeriod, dot11DTIMPeriod,  
dot11AssociationResponseTimeOut,  
dot11DisassociateReason,  
dot11DisassociateStation,  
dot11DeauthenticateReason,  
dot11DeauthenticateStation,  
dot11AuthenticateFailStatus,  
dot11AuthenticateFailStation,  
dot11MultiDomainCapabilityImplemented,  
dot11MultiDomainCapabilityEnabled,  
dot11CountryString,  
dot11SpectrumManagementImplemented,  
dot11SpectrumManagementRequired,  
dot11RSNAOptionImplemented,  
dot11RegulatoryClassesImplemented,  
dot11RegulatoryClassesRequired }  
STATUS current  
DESCRIPTION  
    "The SMTbase5 object class provides the necessary support at the  
    STA to manage the processes in the STA so that the STA may work  
    cooperatively as a part of an IEEE 802.11 network, when the STA is  
    capable of multidomain operation. This object group should be  
    implemented when the multidomain capability option is implemented."  
 ::= { dot11Groups 30 }
```

After Annex H, insert Annex I and Annex J:

Annex I

(informative)

Regulatory classes

I.1 External regulatory references

This annex and Annex J provide information and requirements extending the OFDM PHY specification in Clause 17 for operation in the USA, Europe, and the 4.9 GHz and 5 GHz bands in Japan. The OFDM system provides a WLAN with data payload communication capabilities of 6, 9, 12, 18, 24, 36, 48, and 54 Mbit/s in 20 MHz channels and 3, 4.5, 6, 9, 12, 18, 24, and 27 Mbit/s in 10 MHz channels.

WLANs implemented in accordance with this standard and the specifications and definitions referenced in it are subject to equipment certification and operating requirements established by regional and national regulatory administrations. The specification establishes minimum technical requirements for interoperability, based upon established regulations at the time this standard was issued. These regional and national regulations are subject to revision or may be superseded. Regulatory requirements that do not affect interoperability are not addressed in this standard. Implementers are referred to the regulatory sources in Table I.1 for further information. Operation in countries within defined regulatory domains may be subject to additional or alternative national regulations.

The documents listed in Table I.1 specify the current regulatory requirements for various geographic areas at the time this standard was developed. They are provided for information only and are subject to change or revision at any time.

Table I.1—Regulatory requirement list

Geographic area	Approval standards	Documents	Approval authority
Japan	Ministry of Public Management, Home Affairs, Posts and Telecommunications (MPHPT)	MPHPT Equipment Ordinance (EO) for Regulating Radio Equipment Articles 7, 49.20, 49.21 ^a	MPHPT
United States	Federal Communications Commission (FCC)	CFR47, Part 15, Sections 15.205, 15.209, and 15.247; and Subpart E, Sections 15.401–15.407	FCC
Europe	European Conference of Postal and Telecommunications (CEPT) Administrations and its Electronic Communications Committee (ECC). Also, European Radiocommunications Office, European Telecommunications Standards Institute	ECC DEC (04) 08, ETSI EN301 893	CEPT

^aFrequency planning for licensed STAs in Japan is performed by the regulatory authority and the licensees, addressing the coexistence among STAs operating with a variety of air propagation times and the coexistence between STAs using 20 MHz channel spacing and STAs operating with 10 MHz channel spacing. Note also the CCA mechanism is preserved in licensed operation.

Emissions limits sets are listed in Table I.2, and behavior limits sets are specified in Table I.3. The external regulatory references in Table I.2 and Table I.3 are informative, as they do not specify technical parameters.

Table I.2—Emissions limits sets

Emissions limits set	USA	Europe	Japan
0	Not specified	Not specified	Not specified
1 nomadic use	FCC CFR47, Section 15.407	ETSI EN 301 389-1	MPHPT EO Articles 49.20, 49.21
2 interference-limited areas ^a	Reserved	Reserved	MPHPT EO Article 49.21
3 other interference areas ^a	Reserved	Reserved	MPHPT EO Article 49.21
4–255	Reserved	Reserved	Reserved

^aThe deployment in Japan of licensed radios in dense urban areas (i.e., interference-limited areas) and other areas (i.e., other interference areas) are specified to allow more radios to operate in dense urban areas, while permitting what can be less expensive radio designs to be used elsewhere.

Table I.3—Behavior limits sets

Behavior limits set	USA	Europe	Japan
0	Not specified	Not specified	Not specified
1 nomadic use	FCC CFR47, Section 15.407	ETSI EN 301 389-1	MPHPT EO Articles 49.20, 49.21
2 indoor only use	FCC CFR47, Section 15.407(e)	ETSI EN 301 389-1	MPHPT EO Article 49.20
3 transmit power control	Reserved	ETSI EN 301 389-1	Reserved
4 dynamic frequency selection	Reserved	ETSI EN 301 389-1	Reserved
5 Independent basic service set (IBSS) prohibited	Reserved	Reserved	MPHPT EO Article 49.21
6 4 ms CS ^a	Reserved	Reserved	MPHPT EO Articles 49.20, 49.21
7 licensed base station	Reserved	Reserved	MPHPT EO Article 49.21
8 mobile station	Reserved	Reserved	MPHPT EO Articles 49.20, 49.21
9–255	Reserved	Reserved	Reserved

^aThe Japanese 4 ms CS rule says no STA can transmit for more than 4 ms without carrier sensing, whether transmitting fragments or frames, unless it is controlled by another STA.

I.2 Radio performance specifications

I.2.1 Transmit and receive in-band and out-of-band spurious emissions

Spurious transmissions from compliant devices shall conform to national regulations. For operation in the USA, refer to FCC CFR47, Section 15.407. For operation in Europe, refer to ETSI EN 301 389-1. For operation in Japan, refer to MPHPT EO Article 49.20 and Article 49.21, Section 1.

NOTE—All out-of-band and in-band spurious emission requirements of MPHPT EO Article 49.20 and Article 49.21, Section 1, are included in Table I.4 and Table I.5. Figure I.1 and Figure I.2 are an informative summary of the requirements for operation in the Japanese 4.9 GHz and 5.0 GHz bands.

Table I.4—Japanese out-of-band emission limits

Regulatory domain	Band (GHz)	Out-of-band leakage power	Out-of-band frequencies
For 20 MHz channel spacing systems			
MPHPT EO Article 49.21	4.9	$< 15 \mu\text{W}/\text{MHz}$	$4880 \leq f < 4900 \text{ MHz}$, $5000 < f \leq 5020 \text{ MHz}$
MPHPT EO Article 49.21	5.0	$< 15 \mu\text{W}/\text{MHz}$	$5000 \leq f < 5020 \text{ MHz}$, $5100 < f \leq 5120 \text{ MHz}$
MPHPT EO Article 49.21	5.0	$< 0.5 \text{ mW}/\text{MHz}$	$5020 \leq f < 5030 \text{ MHz}$, $5091 < f \leq 5100 \text{ MHz}$
MPHPT EO Article 49.21, Part 2 in limited interference areas, and unlicensed	4.9	$< 0.2 \mu\text{W}/\text{MHz}$	$4840 \text{ MHz} \pm 10 \text{ MHz}$, $4860 \text{ MHz} \pm 10 \text{ MHz}$
MPHPT EO Article 49.21, Part 2 in limited interference areas, and unlicensed	5.0	$< 0.2 \mu\text{W}/\text{MHz}$	$4960 \text{ MHz} \pm 10 \text{ MHz}$, $4980 \text{ MHz} \pm 10 \text{ MHz}$
MPHPT EO Article 49.20	5.15–5.25	$\leq 2.5 \mu\text{W}/\text{MHz}$	$5130 \leq f \leq 5142 \text{ MHz}$
MPHPT EO Article 49.20	5.15–5.25	$\leq 15 \mu\text{W}/\text{MHz}$	$5142 < f \leq 5150 \text{ MHz}$, $5250 \leq f < 5258 \text{ MHz}$
MPHPT EO Article 49.20	5.15–5.25	$\leq 0.2 \mu\text{W}/\text{MHz}$	$5258 \leq f \leq 5270 \text{ MHz}$
For 10 MHz channel spacing systems			
MPHPT EO Article 49.20	4.9	$< 15 \mu\text{W}/\text{MHz}$	$4895 \leq f < 4905 \text{ MHz}$, $4955 < f \leq 4965 \text{ MHz}$
MPHPT EO Article 49.20	5.0	$< 15 \mu\text{W}/\text{MHz}$	$5015 \leq f < 5025 \text{ MHz}$, $5065 < f \leq 5075 \text{ MHz}$
MPHPT EO Article 49.20	5.0	$< 0.5 \text{ mW}/\text{MHz}$	$5025 \leq f < 5030 \text{ MHz}$

Table I.5—Japanese upper limit of spurious emissions

Regulatory domain	Band (GHz)	Spurious emissions power	Frequencies
For 20 MHz channel spacing systems			
MPHPT EO Article 7	4.9	$\leq 2 \mu\text{W}/\text{MHz}$	$< 4870 \text{ MHz}$
MPHPT EO Article 7	4.9	$\leq 2.5 \mu\text{W}/\text{MHz}$	$4870 \leq f < 4880 \text{ MHz}$, $5020 < f \leq 5270 \text{ MHz}$
MPHPT EO Article 7	4.9	$\leq 0.2 \mu\text{W}/\text{MHz}$	$5270 < f \leq 5342 \text{ MHz}$
MPHPT EO Article 7	4.9	$\leq 1 \mu\text{W}/\text{MHz}$	$> 5342 \text{ MHz}$
MPHPT EO Article 7	5.0	$\leq 2 \mu\text{W}/\text{MHz}$	$< 4990 \text{ MHz}$
MPHPT EO Article 7	5.0	$\leq 2.5 \mu\text{W}/\text{MHz}$	$4990 \leq f < 5000 \text{ MHz}$, $5120 < f \leq 5270 \text{ MHz}$
MPHPT EO Article 7	5.0	$\leq 0.2 \mu\text{W}/\text{MHz}$	$5270 < f \leq 5342 \text{ MHz}$
MPHPT EO Article 7	5.0	$\leq 1 \mu\text{W}/\text{MHz}$	$> 5342 \text{ MHz}$
MPHPT EO Article 7	5.15–5.25	$\leq 2.5 \mu\text{W}/\text{MHz}$	$f < 5130 \text{ MHz}$, $5342 \text{ MHz} < f$
MPHPT EO Article 7	5.15–5.25	$< 0.2 \mu\text{W}/\text{MHz}$	$5270 < f \leq 5342 \text{ MHz}$
For 10 MHz channel spacing systems			
MPHPT EO Article 7	4.9	$\leq 2 \mu\text{W}/\text{MHz}$	$< 4870 \text{ MHz}$
MPHPT EO Article 7	4.9	$\leq 2.5 \mu\text{W}/\text{MHz}$	$4870 \leq f < 4895 \text{ MHz}$, $4965 < f \leq 5270 \text{ MHz}$
MPHPT EO Article 7	4.9	$\leq 0.2 \mu\text{W}/\text{MHz}$	$5270 < f \leq 5342 \text{ MHz}$
MPHPT EO Article 7	4.9	$\leq 1 \mu\text{W}/\text{MHz}$	$> 5342 \text{ MHz}$
MPHPT EO Article 7	5.0	$\leq 2 \mu\text{W}/\text{MHz}$	$< 4990 \text{ MHz}$
MPHPT EO Article 7	5.0	$\leq 2.5 \mu\text{W}/\text{MHz}$	$4990 \leq f < 5015 \text{ MHz}$, $5075 < f \leq 5270 \text{ MHz}$
MPHPT EO Article 7	5.0	$\leq 0.2 \mu\text{W}/\text{MHz}$	$5270 < f \leq 5342 \text{ MHz}$
MPHPT EO Article 7	5.0	$\leq 1 \mu\text{W}/\text{MHz}$	$> 5342 \text{ MHz}$




Figure I.1—Out-of-band and spurious emissions limits for 20 MHz channels in Japan




Figure I.2—Out-of-band and spurious emissions limits for 10 MHz channels in Japan

I.2.2 Transmit power levels

The maximum allowable output power by regulatory domain (except in Japan) is shown in Table I.6.

The maximum allowable output power by Japanese regulatory domain is shown in Table I.7. For the Japanese 4.9 GHz and 5.0 GHz bands, the maximum deviation of designated or rated equivalent isotropically radiated power (EIRP) shall be nominal +20% and nominal -80%.

Table I.6—Transmit power level by regulatory domain

Frequency band (GHz)	USA (Maximum output power with up to 6 dBi antenna gain) (mW)	Europe (EIRP)
5.15–5.25	40 (2.5 mW/MHz)	200 mW
5.25–5.35	200 (12.5 mW/MHz)	200 mW
5.470–5.725	—	1 W
5.725–5.825	800 (50 mW/MHz)	—

Table I.7—Japanese transmit power levels by regulatory domain

Frequency band (GHz)	Regulatory type	Japan
4.9–5.091	Fixed wireless access, licensed	< 250 mW EIRP, and < 50 mW/MHz EIRP for licensed access
4.9–5.091	Nomadic access, unlicensed	< 10 mW/MHz EIRP
5.15–5.25	Unlicensed	< 10 mW/MHz EIRP

I.2.3 Transmit spectrum mask

For operation using 20 MHz channel spacing in the USA, Europe, and Japan, the transmitted spectrum shall have a 0 dBr (dB relative to the maximum spectral density of the signal) bandwidth not exceeding 18 MHz, –20 dBr at 11 MHz frequency offset, –28 dBr at 20 MHz frequency offset, and –40 dBr at 30 MHz frequency offset and above. For operation using 10 MHz channel spacing, the transmitted spectrum shall have a 0 dBr bandwidth not exceeding 9 MHz, –20 dBr at 5.5 MHz frequency offset, –28 dBr at 10 MHz frequency offset, and –40 dBr at 15 MHz frequency offset and above. The measurements shall be made using a 100 kHz resolution bandwidth and a 30 kHz video bandwidth.

For operation in Japan, the average power emitted in adjacent and alternate adjacent channels of the same channel width shall be less than –3 dBr and –18 dBr, respectively, for both the 4.9 GHz and 5.0 GHz bands, measured relative to the EIRP in the 100 kHz at the channel edges and the band edges. For operation in Japan in the 5.15–5.25 GHz band, the average power emitted in adjacent and alternate adjacent channels shall be lower than average on-channel power by 25 dB and 40 dB, respectively.

NOTE—Figure I.3 shows the average power in adjacent channels for 20 MHz channel spacing, and Figure I.4 shows the average power in adjacent channels for 10 MHz channel spacing. There are no special spreading requirements for any particular channel. The alternate adjacent channel(s) are adjacent to the channels adjacent to a given channel.




Figure I.3—Average power in adjacent channels for 20 MHz channel spacing in Japan




Figure I.4—Average power in adjacent channels for 10 MHz channel spacing in Japan

Annex J

(normative)

Country information element and regulatory classes

The Country information element (see 7.3.2.12) allows a STA to configure its PHY and MAC for operation when the regulatory triplet of Regulatory Extension Identifier, Regulatory Class, and Coverage Class fields is present. The regulatory triplet indicates both PHY and MAC configuration characteristics and operational characteristics. The First Channel Number field of subsequent subband triplet(s) is based on the dot11ChannelStartingFactor that is indicated by the Regulatory Class field.

The regulatory class for the OFDM PHY is an index into a set of values for radio equipment sets of rules.

The channel starting frequency variable is a frequency, used together with a channel number, to calculate a channel center frequency.

Channel spacing is the frequency difference between nonoverlapping adjacent channel center frequencies.

The channel set shall be the list of integer channel numbers that are legal for a regulatory domain and class.

The transmit power limit shall be the maximum transmit power that is legal for a regulatory domain and class.

An emissions limits set is an enumerated list of spectral masks and emissions limits that are legal for a regulatory domain and are listed in Table I.1.

Specific transmit restrictions and limits are listed in I.2.

A behavior limits set is an enumerated list of behaviors that are legal for a regulatory domain and are specified in Table I.3.

The regulatory classes specified for 5 GHz operation in the USA are enumerated in Table J.1.

Table J.1—Regulatory classes for 5 GHz bands in the USA

Regulatory class	Channel starting frequency (GHz)	Channel spacing (MHz)	Channel set	Transmit power limit (mW)	Emissions limits set	Behavior limits set
1	5	20	36, 40, 44, 48	40	1	1, 2
2	5	20	52, 56, 60, 64	200	1	1
3	5	20	149, 153, 157, 161	800	1	1
4–255	Reserved	Reserved	Reserved	Reserved	Reserved	Reserved

The regulatory classes specified for 5 GHz operation in Europe are enumerated in Table J.2.

Table J.2—Regulatory classes for 5 GHz bands in Europe

Regulatory class	Channel starting frequency (GHz)	Channel spacing (MHz)	Channel set	Transmit power limit (EIRP)	Emissions limits set	Behavior limits set
1	5	20	36, 40, 44, 48	200	1	2, 3
2	5	20	52, 56, 60, 64	200	1	1, 3, 4
3	5	20	100, 104, 108, 112, 116, 120, 124, 128, 132, 136, 140	1 W	1	1, 3, 4
4–255	Reserved	Reserved	Reserved	Reserved	Reserved	Reserved

The regulatory classes specified for 4.9 GHz and 5 GHz operation in Japan are enumerated in Table J.3.

Table J.3—Regulatory classes for 4.9 GHz and 5 GHz bands in Japan

Regulatory class	Channel starting frequency (GHz)	Channel spacing (MHz)	Channel set	Transmit power limit (dBm)	Emissions limits set	Behavior limits set
1	5	20	34, 38, 42, 46	22	1	1, 2, 6
2	5	20	8, 12, 16	24	2	5, 6, 7
3	5	20	8, 12, 16	24	2	5, 6, 8
4	5	20	8, 12, 16	24	3	5, 6, 7
5	5	20	8, 12, 16	24	3	5, 6, 8
6	5	20	8, 12, 16	22	1	5, 6, 8
7	4	20	184, 188, 192, 196	24	2	5, 6, 7
8	4	20	184, 188, 192, 196	24	2	5, 6, 8
9	4	20	184, 188, 192, 196	24	3	5, 6, 7
10	4	20	184, 188, 192, 196	24	3	5, 6, 8
11	4	20	184, 188, 192, 196	22	1	5, 6, 8
12	5	10	7, 8, 9, 11	24	2	5, 6, 7
13	5	10	7, 8, 9, 11	24	2	5, 6, 8
14	5	10	7, 8, 9, 11	24	3	5, 6, 7

Table J.3—Regulatory classes for 4.9 GHz and 5 GHz bands in Japan (continued)

Regulatory class	Channel starting frequency (GHz)	Channel spacing (MHz)	Channel set	Transmit power limit (dBm)	Emissions limits set	Behavior limits set
15	5	10	7, 8, 9, 11	24	3	5, 6, 8
16	4	10	183, 184, 185, 187, 188, 189	24	2	5, 6, 7
17	4	10	183, 184, 185, 187, 188, 189	24	2	5, 6, 8
18	4	10	183, 184, 185, 187, 188, 189	24	3	5, 6, 7
19	4	10	183, 184, 185, 187, 188, 189	24	3	5, 6, 8
20	4	10	183, 184, 185, 187, 188, 189	17	1	5, 6, 8
21–255	Reserved	Reserved	Reserved	Reserved	Reserved	Reserved