

# IEEE Recommended Practice for Auxiliary Devices for Motors in Class I, Groups A, B, C, and D, Division 2 Locations

*Circuits and Devices*

*Communications Technology*

*Computer*

*Electromagnetics and  
Radiation*

*Energy and Power*

## IEEE Industry Applications Society

Sponsored by the  
Petroleum and Chemical Industry Committee

*Signals and  
Applications*

*Standards  
Coordinating  
Committees*

IEEE Std 303-1991



Published by the Institute of Electrical and Electronics Engineers, Inc., 345 East 47th Street, New York, NY 10017, USA.

October 24, 1991

SH14506

**IEEE**  
**Std 303-1991**  
(Revision of IEEE Std 303-1984)

# **IEEE Recommended Practice for Auxiliary Devices for Motors in Class I, Groups A, B, C, and D, Division 2 Locations**

Sponsor

**Petroleum and Chemical Industry Committee of the  
IEEE Industry Applications Society**

Approved June 27, 1991

**IEEE Standards Board**

**Abstract:** Installation procedures and wiring methods and materials are recommended. Termination housings, motor surge protection, and power-factor-correction capacitors are discussed. The aim is to promote consistent application of the devices covered.

**Keywords:** auxiliary devices for motors, device wiring methods, motor surge protection

The Institute of Electrical and Electronics Engineers, Inc.  
345 East 47th Street, New York, NY 10017-2394, USA

Copyright © 1991 by the  
Institute of Electrical and Electronics Engineers, Inc.  
All rights reserved. Published 1991  
Printed in the United States of America

ISBN 1-55937-142-0

*No part of this publication may be reproduced in any form,  
in an electronic retrieval system or otherwise,  
without the prior written permission of the publisher.*

**IEEE Standards** documents are developed within the Technical Committees of the IEEE Societies and the Standards Coordinating Committees of the IEEE Standards Board. Members of the committees serve voluntarily and without compensation. They are not necessarily members of the Institute. The standards developed within IEEE represent a consensus of the broad expertise on the subject within the Institute as well as those activities outside of IEEE which have expressed an interest in participating in the development of the standard.

Use of an IEEE Standard is wholly voluntary. The existence of an IEEE Standard does not imply that there are no other ways to produce, test, measure, purchase, market, or provide other goods and services related to the scope of the IEEE Standard. Furthermore, the viewpoint expressed at the time a standard is approved and issued is subject to change brought about through developments in the state of the art and comments received from users of the standard. Every IEEE Standard is subjected to review at least every five years for revision or reaffirmation. When a document is more than five years old, and has not been reaffirmed, it is reasonable to conclude that its contents, although still of some value, do not wholly reflect the present state of the art. Users are cautioned to check to determine that they have the latest edition of any IEEE Standard.

Comments for revision of IEEE Standards are welcome from any interested party, regardless of membership affiliation with IEEE. Suggestions for changes in documents should be in the form of a proposed change of text, together with appropriate supporting comments.

**Interpretations:** Occasionally questions may arise regarding the meaning of portions of standards as they relate to specific applications. When the need for interpretations is brought to the attention of IEEE, the Institute will initiate action to prepare appropriate responses. Since IEEE Standards represent a consensus of all concerned interests, it is important to ensure that any interpretation has also received the concurrence of a balance of interests. For this reason IEEE and the members of its technical committees are not able to provide an instant response to interpretation requests except in those cases where the matter has previously received formal consideration.

Comments on standards and requests for interpretations should be addressed to:

Secretary, IEEE Standards Board  
445 Hoes Lane  
P.O. Box 1331  
Piscataway, NJ 08555-1331  
USA

IEEE Standards documents are adopted by the Institute of Electrical and Electronics Engineers without regard to whether their adoption may involve patents on articles, materials, or processes. Such adoption does not assume any liability to any patent owner, nor does it assume any obligation whatever to parties adopting the standards documents.

## Foreword

(This Foreword is not a part of IEEE Std 303-1991, IEEE Recommended Practice for Auxiliary Devices for Motors in Class I, Groups A, B, C, and D, Division 2 Locations.)

This standard was originally published in 1969 and was revised in 1984. In keeping with the goals of maintaining progressive standards, in 1988 the standards group of the IEEE Petroleum and Chemical Industry Committee assigned a working group to revise and update this standard. References to other documentation were corrected. The wording in this standard was modified to reflect changes in other industry standards and to more fully define the intent of this standard.

Suggestions for improvement of this standard are encouraged. These should be addressed to:

Secretary  
IEEE Standards Board  
The Institute of Electrical and Electronics Engineers, Inc.  
345 East 47th Street  
New York, NY 10017

At the time this recommended practice was approved, the 303 Working Group of the Petroleum and Chemical Industry Committee had the following members:

### Barry M. Wood, *Chairman*

J. K. Armintor  
B. H. Campbell

J. A. Oliver

J. A. Robertson  
N. P. Young, Jr.

The following persons were on the balloting committee that approved this recommended practice for submission to the IEEE Standards Board:

E. R. Adams  
J. Armintor  
S. P. Axe  
D. Azbill  
I. Boroumand  
R. Bried  
D. G. Broussard  
M. M. Cameron  
W. F. Casper  
J. M. Daly  
S. M. Dillard  
G. Donner  
R. Doughty  
J. S. Dudor  
M. O. Durham  
J. B. Dwyer  
H. B. Dygert  
C. J. Erickson  
E. J. Fagan

R. W. Gallant  
S. W. Hagemoen  
J. D. Hill  
F. P. Hogan  
R. H. Hulett  
J. Hus  
R. M. Jackson  
M. Johnson  
B. C. Johnson  
J. H. Kassebaum  
P. M. Kinney  
J. C. Lacour  
W. H. Levers  
C. R. Lockerd  
B. W. McCarty  
B. McDaniel  
P. W. Myers  
R. L. Nailen

R. A. Neil  
J. P. Nelson  
J. B. Overmeyer  
T. P. Pearson  
B. M. Polkinghorn  
J. P. Propst  
M. H. Ramsey  
Q. Reynolds  
S. W. Shannon  
P. J. Skobel  
A. W. Smith  
T. B. Smith  
H. R. Stewart  
E. B. Turner  
D. Vardeman  
A. E. Whiteside  
B. Wiseman  
J. R. Zahn  
P. Zotos

When the IEEE Standards Board approved this recommended practice on June 27, 1991, it had the following membership:

### Marco W. Migliaro, *Chairman*

### Donald C. Loughry, *Vice Chairman*

### Andrew G. Salem, *Secretary*

Dennis Bodson  
Paul L. Borrill  
Clyde Camp  
James M. Daly  
Donald C. Fleckenstein  
Jay Forster\*  
David F. Franklin  
Ingrid Fromm

Thomas L. Hannan  
Donald N. Heirman  
Kenneth D. Hendrix  
John W. Horch  
Ben C. Johnson  
Ivor N. Knight  
Joseph L. Koepfinger\*  
Irving Kolodny  
Michael A. Lawler

John E. May, Jr.  
Lawrence V. McCall  
Donald T. Michael\*  
Stig L. Nilsson  
John L. Rankine  
Ronald H. Reimer  
Gary S. Robinson  
Terrance R. Whittemore

\*Member Emeritus

Peter Arnold  
IEEE Standards Project Editor

## Contents

SECTION	PAGE
1. Scope .....	5
2. Purpose .....	5
3. References .....	5
4. Definitions .....	6
5 Device Installation Recommendations .....	6
5.1 motor auxiliary device categories	
5.2 motor auxiliary devices containing a make or break contact, or both	
5.3 devices without a make or break contact, or both	
6. Device Wiring Methods and Materials .....	7
7 Terminal Housings .....	7
8 Motor Surge Protection .....	7
9. Power-Factor Correction Capacitors .....	8

# IEEE Recommended Practice for Auxiliary Devices for Motors in Class I, Groups A, B, C, and D, Division 2 Locations

## 1. Scope

This recommended practice is limited to auxiliary devices associated with motors operating in Division 2 areas, classified as Class I, Groups A, B, C, and D locations. This recommended practice is not an attempt to rewrite or otherwise supersede application sections of ANSI/NFPA 70-1990 [1],<sup>1</sup> or any other codes or ordinances. Rather, it is intended to serve as a supplement to existing codes that in this area are not sufficiently specific to serve as a guide to good engineering practice. The guidance contained herein, therefore, is in addition to the ANSI/NFPA 70-1990 requirements for wiring systems for hazardous (classified) locations.

## 2. Purpose

The following information is intended to bring together a brief description of basic electrical practices in regard to the application and installation of auxiliary devices to motors operating in Class I, Groups A, B, C, and D, Division 2 locations. It should be understood that this information is only a guide to promote consistent application of such devices and must be used with sound engineering judgment.

<sup>1</sup>The numbers in brackets correspond to those of the references listed in Section 3.

## 3. References

This recommended practice shall be used in conjunction with the following publications:

[1] ANSI/NFPA 70-1990, National Electrical Code.<sup>2</sup>

[2] ANSI/NFPA 496-1989, Purged and Pressurized Enclosures for Electrical Equipment.

[3] ANSI/NFPA 497A-1986, Classification of Class I Hazardous (Classified) Locations for Electrical Installations in Chemical Process Areas.

[4] API-RP500-1991 Classification of Locations for Electrical Installations in Petroleum Facilities.<sup>3</sup>

<sup>2</sup>NFPA documents are available from the Publication Sales, National Fire Protection Association, 1 Batterymarch Park, Quincy, MA 02269-9101, USA. This document is also available from the Sales Department, American National Standards Institute, 11 West 42nd St., New York, NY 10036, USA.

<sup>3</sup>API documents are available from the American Petroleum Institute, 1220 L Street, Northwest, Washington, DC 20005.

#### 4. Definitions

**auxiliary devices.** Components installed either integrally within the motor, located adjacent to or mounted on the motor, or attached to its terminals for the purpose of monitoring the operating conditions or protecting the motor. Refer to 5.2 and 5.3 for examples.

**Class I, Division 2 Locations.** Basically those in which there may be flammable gas present due to a failure of a process system. Under normal conditions a flammable mixture of gas is not present.

For a complete definition, refer to the latest edition of ANSI/NFPA 70-1990 [1], Chapter 5, Article 500. For a guide in establishing the limits of these locations, refer to API-RP500-1991 [4] and ANSI/NFPA 497A-1986 [3].

#### 5. Device Installation Recommendations

**5.1 Motor Auxiliary Device Categories.** For installation requirements, auxiliary devices generally fall in one of two categories:

- (1) Devices containing a make or break contact, or both (arcing devices).
- (2) Devices without a make or break contact, or both (non-arcing devices).

**5.2 Motor Auxiliary Devices Containing a Make or Break Contact, or Both.** Included are bearing temperature switches or relays, certain types of motor winding temperature sensors, vibration switches, air filter differential pressure switches, zero speed switches, leak detector relays, and other types of relays or switches either mounted inside a motor where there is a free exchange of ambient atmosphere or outside the motor housing.

These devices must be installed in enclosures suitable for the application class, group, and division (e.g., Class I, Group D, Division 2). If the enclosure will be subject to outdoor weather conditions, the enclosure should be additionally designed for the stated conditions. General purpose enclosures are permitted if any of the following conditions is satisfied:

- (1) Contacts are immersed in oil.
- (2) Circuits are intrinsically safe, ANSI/NFPA 70-1990 [1], Articles 500 and 504.
- (3) Circuits are nonincendive, ANSI/NFPA 70-1990 [1], Article 501-3(b) (exception c).
- (4) Enclosure is pressurized, ANSI/NFPA 496-1989 [2].
- (5) Contacts are mounted in a hermetically sealed chamber.

Specifically with regard to Item (5), if the device is susceptible to mechanical, chemical, or other environmental types of damage that may result in the possibility of exposing the contact structure to the surrounding atmosphere, appropriate precautions must be taken to prevent its occurrence. Furthermore, the contact circuit must be adequately protected to ensure that a short circuit anywhere in the contact circuit will not damage the contact structure or enclosure.

**5.3 Devices without a Make or Break Contact, or Both.** Included in this category are resistance temperature detectors, space heaters, current transformers, motor surge capacitors, gapless type arresters, noncontacting shaft vibration probes and their oscillator/demodulators (drivers), and other devices that do not arc during normal operation. Such devices installed either inside or outside of the motor housing may be of the general-purpose type unless other environmental considerations dictate the use of a specific enclosure especially designed for operation in that environment.

**5.3.1** Space heaters should produce sufficient heat to prevent moisture condensation on the motor windings. However, the temperature of all space heaters should not exceed 80% of the auto ignition temperature of the gas or vapor involved when continuously energized at rated voltage at the maximum rated ambient air temperature.

**5.3.2** Space heaters must be so constructed as to be unaffected by the accumulation of moisture and should have terminals adequately protected against moisture under severe weather conditions. Space heaters should be mounted on noncombustible material and should operate without thermal damage to the motor or themselves. The maximum surface

temperature of space heaters should be indicated on the space heater nameplate or on an auxiliary nameplate mounted on the space heater terminal box. A cautionary note that replacement heaters must not have a surface temperature greater than this nameplate value should be included. These recommendations supplement the requirements in ANSI/NFPA-70-1990 [1], Article 501.

## 6. Device Wiring Methods and Materials

**6.1** The general and specific rules of ANSI/NFPA70-1990 [1] with regard to wiring methods are not intended to apply to internal motor wiring. Refer to ANSI/NFPA 70-1990 [1], Article 300-1(b). It is suggested that the user notify the manufacturer of any specific environmental considerations that dictate the use of a specific wiring material especially designed for operation in that environment.

**6.2** Device wiring located outside the motor should meet the requirements of ANSI/NFPA-70-1990 [1], Article 501, pertaining to wiring methods and installations.

## 7. Terminal Housings

**7.1** These terminal housings are in the category of junction boxes containing no arcing devices and as such are not required to be explosionproof. See ANSI/NFPA70-1990 [1], Article 501.

**7.2** When auxiliary devices are to be mounted in a terminal housing, the housing should be designed to permit ready access to all parts for maintenance and inspection. The terminal housing should be designed with ample space for mounting of and wiring to the auxiliary devices.

**7.3** The construction of the terminal housing is basically determined by environmental conditions other than the hazardous (classified) location.

**7.4** If a locknut-bushing attachment is used instead of a threaded fitting, a bonding jumper must be provided across the junction to provide

a continuous path of adequate capacity for ground-fault currents that may pass through the junction. Refer to ANSI/NFPA 70-1990 [1], Articles 250-78 and 501.

**7.5** Control, relay, and ammeter conductors used in connection with any motor may occupy the same terminal housing as the motor circuit conductors only if the motor voltage does not exceed 600 V. Refer to ANSI/NFPA 70-1990 [1], Article 300-3(c).

**7.6** If the rated motor voltage exceeds 600 V, accessory leads should terminate in a terminal box or boxes separate from the motor terminal housing. As an exception, current and potential transformers located in the motor terminal housing may be permitted to have their secondary connections terminated in the motor terminal housing if separated from the motor leads by a suitable physical barrier to prevent accidental contact. The physical barrier should provide the equivalent of a separate terminal housing except for the common external cover.

**7.7** Motor surge protective equipment may occupy the same terminal housing as the motor circuit conductors provided such equipment will, under normal operating conditions, not be exposed to temperatures beyond its ratings.

**7.8** Motors may have windings and auxiliary devices terminated within the motor enclosure, provided such terminations are conveniently accessible and are protected against mechanical damage and accidental contact by personnel.

## 8. Motor Surge Protection

**8.1** Motor surge protection equipment, consisting of surge arresters and surge capacitors, does not replace nor is it intended that it be substituted for similar equipment required for the electrical system by ANSI/NFPA70-1990 [1], Articles 230-209 and 280.

**8.2** When motor surge protection is installed at the motor, every effort should be made to keep the conductors between the motor terminals and the surge protection, and between the surge

IEEE  
Std 303-1991

protection equipment and ground, shorter than 3 ft (0.9 m).

**8.3** When motor surge-protective equipment is installed in a metal enclosure other than the motor terminal housing, a general purpose enclosure, requiring tools for access and provided with a suitable warning plate may be used.

**8.4** Motor surge arresters should be the gapless (typically metal-oxide) type with sealed construction to confine normal electric discharges within themselves.

**8.5** Motor surge capacitors should be of a sealed type especially designed for surge-protective duty.

**8.6** Ground terminals of motor surge protective equipment must be connected to the motor

(equipment) grounding terminal located within the terminal housing using a conductor sized in accordance with ANSI/NFPA70-1990 [1], Article 280. The surge protective equipment and the stator support structure should be connected to the motor (equipment) grounding terminal by the shortest practical route.

### **9. Power Factor Correction Capacitors**

A power-factor correction capacitor installation that meets the installation requirements as outlined in ANSI/NFPA 70-1990 [1], Article 460, will be acceptable for installation in Class I, Division 2 locations, except that any overcurrent device, disconnecting means, and associated wiring that may be provided with the capacitors should conform to the requirements of ANSI/NFPA 70-1990 [1], Article 501.

## Learn how to Apply Standards at IEEE Power Standards Seminars

IEEE Seminars — Keeping You Competitive through Industry Standards

With today's trend toward standardization, it's *vital* to know what standards effect you and your industry. But to advance your professional skills and the competitive stature of your organization, you need to *know* your standards and *how* to apply them in your environment.

To serve your application needs, IEEE offers specialized seminars that provide the fundamentals of using specific standards.

### IEEE Power Engineering Seminars

The IEEE sponsors seminars on the Color Books and other power engineering standards throughout the year.

Our seminars include:

- Human Factors Engineering at Nuclear Plants
- Large Storage Batteries for Stationary Use
- Protection of Co-Generation Plants Paralleled with Utility Transmission Systems
- Health Care Facilities Power Systems
- Planning, Design, Protection, Maintenance, and Operation of Industrial and Commercial Power Systems
- Electric Power Supply Systems for Nuclear Power Generating Stations

*Special team discounts are available. IEEE-sponsored seminars may also be brought to your plant. For details, write to the IEEE Standards Seminar Manager, 445 Hoes Lane, PO Box 1331, Piscataway, NJ 08855-1331 USA. Or call us Toll Free in the U.S and Canada at 1-800-678-IEEE and ask for Standards Seminars and Training Programs. Outside the U.S. and Canada, please call 908-562-3805.*

ISBN 1-55937-142-0