



INTERNATIONAL TELECOMMUNICATION UNION

ITU-T

TELECOMMUNICATION
STANDARDIZATION SECTOR
OF ITU

Q.318

**SPECIFICATIONS OF SIGNALLING SYSTEM R1
LINE SIGNALLING**

**DOUBLE SEIZING WITH BOTH - WAY
OPERATION**

ITU-T Recommendation Q.318

(Extract from the *Blue Book*)

NOTES

1 ITU-T Recommendation Q.318 was published in Fascicle VI.4 of the *Blue Book*. This file is an extract from the *Blue Book*. While the presentation and layout of the text might be slightly different from the *Blue Book* version, the contents of the file are identical to the *Blue Book* version and copyright conditions remain unchanged (see below).

2 In this Recommendation, the expression “Administration” is used for conciseness to indicate both a telecommunication administration and a recognized operating agency.

Recommendation Q.318

2.8 DOUBLE SEIZING WITH BOTH-WAY OPERATION

2.8.1 *General*

To minimize the probability of double seizing, the circuit selection at the two ends of both-way circuit groups should be such that, as far as possible, double seizing can occur only when a single circuit of the group remains free (e.g. by selection of circuits in opposite order at the two ends of the circuit group).

2.8.2 *Unguarded interval*

In general the unguarded interval is small, except in the case of satellite operation where the circuit propagation time is long. However, System R1 does provide a means of detecting double seizing.

2.8.3 *Detection of double seizing*

In the event of double seizing, the incoming connect (seizing) signal is recognized at each end as a delay-dialling signal. If a start-dialling (proceed-to-send) signal is not received within the time-out interval (e.g. 5 seconds) double seizing is assumed.

In this event, either of the following arrangements may apply:

- a) an automatic repeat attempt to set up the call; or
- b) a recorder indication is given to the operator or to the calling subscriber and no automatic repeat attempt is made.

With either method, means must be provided to ensure positive release of the double seized circuit. To achieve the release it is recommended that the office which first assumes (based on timing) that dual seizure has occurred transmits a tone-on (0 state) signal followed by a tone-off (1 state) signal before the final tone-on (0 state) signal (disconnect) is sent. The duration of initial tone-on (0 state) signal should be a minimum of 100 ms and a maximum of 200 ms. The tone-off (1 state) signal should be recognized as an unexpected tone-off (1 state) signal at the distant end, after which the action specified in § 3.6.2, 1) c) of Recommendation Q.325 applies.